

Australian Capital Territory

Electricity Safety Act 1971

A1971-30

Republication No 23 Effective: 6 March 2014 – 17 April 2014

Republication date: 6 March 2014

Last amendment made by A2014-2

Authorised by the ACT Parliamentary Counsel

About this republication

The republished law

This is a republication of the *Electricity Safety Act 1971* (including any amendment made under the *Legislation Act 2001*, part 11.3 (Editorial changes)) as in force on 6 March 2014. It also includes any commencement, amendment, repeal or expiry affecting this republished law to 6 March 2014.

The legislation history and amendment history of the republished law are set out in endnotes 3 and 4.

Kinds of republications

The Parliamentary Counsel's Office prepares 2 kinds of republications of ACT laws (see the ACT legislation register at www.legislation.act.gov.au):

- authorised republications to which the Legislation Act 2001 applies
- unauthorised republications.

The status of this republication appears on the bottom of each page.

Editorial changes

The *Legislation Act 2001*, part 11.3 authorises the Parliamentary Counsel to make editorial amendments and other changes of a formal nature when preparing a law for republication. Editorial changes do not change the effect of the law, but have effect as if they had been made by an Act commencing on the republication date (see *Legislation Act 2001*, s 115 and s 117). The changes are made if the Parliamentary Counsel considers they are desirable to bring the law into line, or more closely into line, with current legislative drafting practice.

This republication includes amendments made under part 11.3 (see endnote 1).

Uncommenced provisions and amendments

If a provision of the republished law has not commenced, the symbol [U] appears immediately before the provision heading. Any uncommenced amendments that affect this republished law are accessible on the ACT legislation register (www.legislation.act.gov.au). For more information, see the home page for this law on the register.

Modifications

If a provision of the republished law is affected by a current modification, the symbol [M] appears immediately before the provision heading. The text of the modifying provision appears in the endnotes. For the legal status of modifications, see the *Legislation Act 2001*, section 95.

Penalties

At the republication date, the value of a penalty unit for an offence against this law is \$140 for an individual and \$700 for a corporation (see *Legislation Act 2001*, s 133).



Electricity Safety Act 1971

Contents

		Page
Part 1	Preliminary	
1	Name of Act	2
2	Dictionary	2
3	Notes	2
ЗA	Offences against Act—application of Criminal Code etc	3
Part 2	Electrical wiring work and electrical installations	
Part 2		4
	installations	4
4	installations Connecting electrical installations to network—inspections	•

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 contents 1

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

Contents

Part 3	Prescribed articles of electrical equipment	Page
Division :		
9	Definitions for pt 3	8
10	Declaration of corresponding law	8
Division :		0
11		0
11A	Meaning of prescribed articles of electrical equipment	9 9
11A 11B	Declaration of prescribed articles of electrical equipment	
12	Declaration of articles not prescribed articles of electrical equipment Sale or installation of prescribed articles	10 10
12	·	10
13	Sale or installation of noncomplying prescribed articles	12
14	Registration as approved first seller	14
15	Application for registration of declaration of compliance	14
17	Registration of declaration of compliance Suspension or cancellation of registration of declaration of compliance	
18		18
10	Transfer of registration of declaration of compliance Safety registration mark	19
20	Approved testing laboratories	19
20	Registers	20
21	Examination and testing of articles	20
	-	22
Division 3		23
23 24	False representation	23 23
24	Evidence of registration of declaration of compliance	23
Part 4	Non-prescribed articles of electrical equipment	
25	Articles to which pt 4 applies	24
26	Minimum safety standards	24
27	Offences—energy efficiency requirements for non-prescribed articles	
	of electrical equipment	25
Part 5	Defective articles of electrical equipment	
28	Prohibited articles	27
29	Sale or installation of prohibited articles	27
30	Directions about unsafe articles	28
31	Publication of safety warnings	29
contents 2	Electricity Safety Act 1971	R23
	Effective: 06/03/14-17/04/14 00	6/03/14

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

		Contents
		Page
Part 6	Serious electrical accidents	Ũ
32	Definitions for pt 6	30
33	Reporting by occupiers and electrical contractors	30
34	Reporting by electricity distributor	31
35	Interference with site of serious electrical accident	31
36	Publication of report of serious electrical accident	32
Part 7	Enforcement	
Division	7.1 General	
37	Definition of business premises	33
38	Things connected with offences	33
39	Planning and land authority may require information and documents	33
40	Contravention of requirement by planning and land authority	34
41	Appointment of inspectors	34
42	Identity cards	35
Division	7.2 Inspectors' powers	
43	General power to enter premises	36
44	Production of identity card	36
45	Consent to entry	37
46	Warrants	38
47	Warrants—application made other than in person	39
48	Powers on entry to premises	40
49	Powers in relation to serious electrical accidents	41
50	Powers in relation to unsafe articles of electrical equipment	42
51	Disconnecting etc dangerous electrical equipment and installations	43
52	Power to require name and address	43
53	Power to seize evidence	44
54	Receipt for things seized	45
55	Access to things seized	45
56	Return of things seized	46
57	Power to inspect electrical wiring work	46
Division	7.3 Miscellaneous	
58	Self-incrimination etc	47
59	Damage etc to be minimised	48
R23	Electricity Safety Act 1971 c	ontents 3

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

Effective: 06/03/14-17/04/14

06/03/14

\sim		
ι.n	nte	nts

60	Compensation	Page 48
Part 8	Notification and review of decisions	
61	Meaning of reviewable decision-pt 8	49
62	Reviewable decision notices	49
62A	Applications for review	49
Part 9	Miscellaneous	
63	Evidence	50
64	Determination of fees	51
65	Approved forms	51
66	Regulation-making power	51
Schedu	Ile 1 Reviewable decisions	53
Dictionary		
Endnote	S	
1	About the endnotes	60
2	Abbreviation key	60
3	Legislation history	61
4	Amendment history	68
5	Earlier republications	106
6	Renumbered provisions	107

contents 4

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14

R23 06/03/14

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au



Electricity Safety Act 1971

An Act relating to the safe use of electricity, and for other purposes

R23 06/03/14

page 1

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

Part 1 Preliminary

Section 1

Part 1 Preliminary

1 Name of Act

This Act is the *Electricity Safety Act 1971*.

2 Dictionary

The dictionary at the end of this Act is part of this Act.

Note 1 The dictionary at the end of this Act defines certain terms used in this Act, and includes references (*signpost definitions*) to other terms defined elsewhere.

For example, the signpost definition '*electricity distributor*—see the *Utilities Act 2000*, dictionary.' means that the term 'electricity distributor' is defined in that Act and the definition applies to this Act.

Note 2 A definition in the dictionary (including a signpost definition) applies to the entire Act unless the definition, or another provision of the Act, provides otherwise or the contrary intention otherwise appears (see Legislation Act, s 155 and s 156 (1)).

3 Notes

A note included in this Act is explanatory and is not part of this Act.

Note See the Legislation Act, s 127 (1), (4) and (5) for the legal status of notes.

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

3A Offences against Act—application of Criminal Code etc

recklessness and strict liability).

Other legislation applies in relation to offences against this Act.

Note 1 Criminal Code
 The Criminal Code, ch 2 applies to all offences against this Act (see Code, pt 2.1).
 The chapter sets out the general principles of criminal responsibility (including burdens of proof and general defences), and defines terms used for offences to which the Code applies (eg conduct, intention,

Note 2 Penalty units

The Legislation Act, s 133 deals with the meaning of offence penalties that are expressed in penalty units.

Section 4

Part 2 Electrical wiring work and electrical installations

4 Connecting electrical installations to network inspections

- (1) A person commits an offence if—
 - (a) the person connects a new electrical installation to an electricity network; and
 - (b) the installation has not been inspected, tested and passed by an inspector.

Maximum penalty: 50 penalty units, imprisonment for 6 months or both.

(2) This section does not apply in circumstances prescribed by regulation.

5 Compliance with AS/NZS 3000

- (1) A person commits an offence if—
 - (a) the person carries out electrical wiring work; and
 - (b) the work does not comply with AS/NZS 3000 as in force—
 - (i) when the work is completed; or
 - (ii) if the work is not completed—when the work is carried out.

Maximum penalty: 50 penalty units.

- (2) An offence against this section is a strict liability offence.
- (3) This section does not apply to—
 - (a) electrical wiring work that consists only of—

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

- (i) the disconnection of an appliance or a fitting; or
- (ii) the disconnection and reconnection of an appliance or a fitting if the electrical load is not increased; or
- (iii) the replacement of an appliance or a fitting if the electrical load is not increased; or
- (b) electrical wiring work prescribed by regulation; or
- (c) electrical wiring work carried out in circumstances prescribed by regulation.
- (4) In this section:

fitting means a switch, lighting point or socket outlet.

6 Testing and reporting of electrical work

- (1) A person who carries out electrical wiring work commits an offence if—
 - (a) the person does not ensure that the work—
 - (i) is tested in accordance with AS/NZS 3017 as in force when the test is carried out; and
 - (ii) complies with AS/NZS 3000 when the test is carried out; or
 - (b) within 14 days after the day the test is carried out, the person does not give the construction occupations registrar, or the owner of the installation for which the work was done, a report of the test in a form approved by the registrar under section 65.

Maximum penalty: 5 penalty units.

- (2) Subsection (1) does not apply to—
 - (a) electrical wiring work prescribed by regulation; or
 - (b) electrical wiring work carried out in circumstances prescribed by regulation.

Section 8

Part 2

8

- (3) A person who has given the construction occupations registrar a report under subsection (1) (b) commits an offence if—
 - (a) the registrar asks the person, in writing and within 2 years after receiving the report, for a copy of the report; and
 - (b) the person does not give a copy of the report to the registrar within 14 days after the day the request is made.

Maximum penalty: 5 penalty units.

(4) An offence against this section is a strict liability offence.

Directions to rectify unsafe installations

- (1) This section applies if an inspector believes on reasonable grounds that—
 - (a) an electrical installation is unsafe or has not been inspected, tested and passed as required under this part; or
 - (b) electrical wiring work is unsafe or has not been carried out, or tested, as required under this part.
- (2) The inspector may give the person who has carried out the electrical wiring work relevant for subsection (1) (a) or (b) a written direction to take stated action to make the installation or work safe and compliant with this part.
- (3) The direction may also require the person to give the inspector written information about the installation or work.

Examples

- 1 a written report about a test required in the direction by the person who did the test
- 2 an electrical engineer's report about whether work complies with relevant standards
- *Note* An example is part of the Act, is not exhaustive and may extend, but does not limit, the meaning of the provision in which it appears (see Legislation Act, s 126 and s 132).

R23 06/03/14

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

(4) Without limiting the operation of subsection (2), a direction may require the disconnection or isolation of the relevant part of the installation or wiring so that it cannot receive a supply of electricity.

- (5) Subsection (6) applies if—
 - (a) the direction requires the person who carried out the electrical wiring work to do a thing; and
 - (b) the person—
 - (i) is not licensed, authorised or qualified to do the thing; or
 - (ii) if a licence, authorisation or qualification is not required to do the thing—does not have appropriate experience and skill to do the thing.
- (6) The person must arrange, and pay for, the thing to be done by someone who—
 - (a) is licensed, authorised or qualified to do the thing; or
 - (b) if a licence, authorisation or qualification is not required to do the thing—has appropriate experience and skill to do the thing.
- (7) A person must not engage in conduct that contravenes a direction under subsection (2).

Maximum penalty: 50 penalty units, imprisonment for 6 months or both.

Note For inspectors' power to disconnect a dangerous installation, see s 51 (1) (b).

Part 3 Prescribed articles of electrical equipment

Division 3.1 Preliminary

9 Definitions for pt 3

In this part:

approved first seller means a person registered under section 14 (2).

corresponding law, in relation to a State or another Territory, means a law of that State or Territory declared under section 10 (Declaration of corresponding law).

declaration of compliance, in relation to a prescribed article of electrical equipment, means a declaration that the article complies with—

- (a) prescribed standards; or
- (b) standards specified in a corresponding law of a State or another Territory.

relevant safety standard, for an article of electrical equipment, means the safety standard stated under section 11A (3) for the article.

10 Declaration of corresponding law

- (1) The Minister may declare a specified law of a State or another Territory, being a law that contains provisions substantially similar to this part, to be a corresponding law for this part.
- (2) A declaration is a notifiable instrument.

Note A notifiable instrument must be notified under the *Legislation Act 2001*.

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

Division 3.2 Regulation of dealings

11 Meaning of *prescribed article of electrical equipment*

In this Act:

prescribed article of electrical equipment—

- (a) means an article of electrical equipment declared under section 11A; but
- (b) does not include an article of electrical equipment declared under section 11B.

11A Declaration of prescribed articles of electrical equipment

- (1) The planning and land authority may declare that an article of electrical equipment is a prescribed article of electrical equipment.
- (2) However, the planning and land authority must not make a declaration about an article of electrical equipment under subsection (1) unless satisfied that there are reasonable grounds for believing that—
 - (a) because of its design or construction, the article is, or is likely to become, unsafe to use; and
 - (b) because of the risk of death or injury to people or the risk of damage to property, the article should be declared to be a prescribed article of electrical equipment.
- (3) A declaration under subsection (1) about an article of electrical equipment must state the safety standard that the article must comply with.
- (4) Without limiting subsections (1) and (3), the planning and land authority may declare an article of electrical equipment under subsection (1), or state the safety standard that an article of electrical equipment must comply with, by adopting a law of a State, as in

force at a particular time or from time to time, under which the article or safety standard is prescribed.

(5) A declaration under subsection (1) is a notifiable instrument.

Note A notifiable instrument must be notified under the Legislation Act.

11B Declaration of articles not prescribed articles of electrical equipment

- (1) The planning and land authority may declare that an article of electrical equipment is not a prescribed article of electrical equipment.
- (2) Without limiting subsection (1), the planning and land authority may declare an article of electrical equipment under subsection (1) by adopting a law of a State, as in force at a particular time or from time to time, under which the article is prescribed.
- (3) A declaration under subsection (1) is a notifiable instrument.

Note A notifiable instrument must be notified under the Legislation Act.

12 Sale or installation of prescribed articles

- (1) An approved first seller commits an offence if—
 - (a) the seller—
 - (i) sells a prescribed article of electrical equipment (a *prescribed article*); or
 - (ii) installs a prescribed article in, or connects a prescribed article to, an electrical installation; and
 - (b) the seller is reckless about whether the article is a prescribed article and—
 - (i) a declaration of compliance in relation to the article is not registered under section 16 or the corresponding law of a State or another Territory; or

R23 06/03/14

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

(ii) a direction under section 30 (Directions about unsafe articles) has been given to the seller in relation to articles of the same brand and model.

Maximum penalty: 200 penalty units.

- (2) A person, other than an approved first seller, commits an offence if—
 - (a) the person—
 - (i) sells a prescribed article; or
 - (ii) installs a prescribed article in, or connects a prescribed article to, an electrical installation; and
 - (b) the person is reckless about whether the article is a prescribed article and—
 - (i) a declaration of compliance in relation to the article had never been registered under section 16 or the corresponding law of a State or another Territory; or
 - (ii) the person has received from someone else a notice under section 30 in relation to the recall of articles of the same brand and model.

Maximum penalty: 200 penalty units.

13 Sale or installation of noncomplying prescribed articles

A person commits an offence if-

- (a) the person—
 - (i) sells a prescribed article of electrical equipment (a *prescribed article*); or
 - (ii) installs a prescribed article in, or connects a prescribed article to, an electrical installation; and

- (b) the prescribed article does not comply with the standards mentioned in the relevant declaration of compliance; and
- (c) the person is reckless about whether the prescribed article complies.

Maximum penalty: 200 penalty units.

14 Registration as approved first seller

- (1) A person who—
 - (a) manufactures prescribed articles of electrical equipment in the ACT; or
 - (b) imports prescribed articles of electrical equipment into the ACT from outside Australia;

may apply in writing to the construction occupations registrar to be registered as an approved first seller in relation to those articles.

Note A fee may be determined under s 64 (Determination of fees) for this subsection.

- (2) Subject to subsection (3), the construction occupations registrar must, on receiving an application under subsection (1), register the applicant as an approved first seller in relation to the prescribed articles of electrical equipment specified in the application by causing the prescribed particulars in relation to the applicant and those articles to be entered in the register referred to in section 21 (1) (b).
- (3) The construction occupations registrar may refuse to register an applicant as an approved first seller if the registrar is satisfied that the applicant—
 - (a) is insolvent; or
 - (b) has been refused registration as a first seller or an approved applicant, or equivalent registration, under the corresponding law of a State or another Territory; or

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

- (c) has been registered as a first seller or an approved applicant or has equivalent registration under the corresponding law of a State or another Territory and that registration has been cancelled otherwise than at the request of the applicant; or
- (d) has been convicted of an offence against this part, against part 3 as in force immediately before the commencement of this part or of a similar offence against the law of a State or another Territory; or
- (e) has not complied with the other requirements (if any) that are prescribed.
- (4) The construction occupations registrar may cancel the registration of a person as an approved first seller if—
 - (a) the registrar is satisfied that—
 - (i) the person is insolvent; or
 - (ii) the person has been refused registration as a first seller or approved applicant, or equivalent registration, under a corresponding law of a State or another Territory; or
 - (iii) the registration of the person as a first seller or approved applicant, or equivalent registration of the person, under the corresponding law of a State or another Territory has been cancelled otherwise than at the request of the person; or
 - (iv) the person has been convicted of an offence against this part or part 3 as in force immediately before the commencement of this part or of a similar offence against the law of a State or another Territory; or
 - (v) the person has supplied an article of electrical equipment in breach of an undertaking referred to in section 15 (3) (d); or

- (b) the approved first seller requests in writing that the registration be cancelled; or
- (c) the approved first seller—
 - (i) for a body corporate—is dissolved; or
 - (ii) for an individual—dies.
- (5) For this section, a person is taken to be insolvent if—
 - (a) for a body corporate—a resolution for the winding-up of the body has been passed or an application for the winding-up of the body has been filed in a court; or
 - (b) for an individual—the person becomes bankrupt or personally insolvent.
- (6) An approved first seller commits an offence if—
 - (a) there is a change in the prescribed particulars mentioned in subsection (2) in relation to the seller; and
 - (b) the seller fails to give written notice of the change to the construction occupations registrar within 7 days after the day of the change.

Maximum penalty: 20 penalty units.

(7) The construction occupations registrar must cause particulars of any change notified under subsection (6) to be entered in the register referred to in subsection (2).

15 Application for registration of declaration of compliance

- (1) An approved first seller may apply to the construction occupations registrar for the registration of a declaration of compliance made by that seller in relation to a prescribed article of electrical equipment by lodging with the registrar
 - (a) a written application; and

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

- (b) the declaration of compliance; and
- (c) a report prepared by a testing laboratory approved for this Act to the effect that the article has been tested and found to comply with the relevant safety standards; and
- (d) subject to subsection (2), the article or another article of the same brand and model.
- *Note* A fee may be determined under s 64 (Determination of fees) for this subsection.
- (2) If it is impracticable to lodge an article with the construction occupations registrar under subsection (1) (d), the approved first seller must give the registrar reasonable access to the article.
- (3) A declaration of compliance lodged under this must contain—
 - (a) the name and business address of the approved first seller; and
 - (b) a description of the article of electrical equipment to which it relates, identifying the article by the manufacturer's model or catalogue number or by any other means the construction occupations registrar determines; and
 - (c) a declaration by the applicant that the article complies with the relevant safety standards; and
 - (d) an undertaking by the applicant that, while the declaration of compliance is in force, the applicant will not supply an article of electrical equipment of the same description, type or class imported or manufactured by the applicant to any person unless—
 - (i) the article of electrical equipment complies with the relevant safety standards; and
 - (ii) the article of electrical equipment is marked, stamped or labelled as prescribed; and

- (iii) if the article of electrical equipment has been modified in any way—details of the modification have been recorded in the register referred to in section 21 (1) (c) or a new declaration of compliance in relation to that article has been registered; and
- (e) any other information required by the construction occupations registrar.
- *Note* If a form is approved under s 65 (Approved forms) for a declaration of compliance, the form must be used.

16 Registration of declaration of compliance

- (1) Subject to subsection (2), if the construction occupations registrar is satisfied that a prescribed article of electrical equipment in relation to which a declaration of compliance has been lodged under section 15 complies with the requirements of the relevant safety standards, the registrar must register the declaration of compliance in the name of the approved first seller who lodged it by entering the prescribed particulars in relation to that declaration in the register referred to in section 21 (1) (c).
- (2) A declaration of compliance in relation to an article of electrical equipment must not be registered under this section if registration of a declaration of compliance in relation to an article of the same brand and model has been refused under the corresponding law of a State or another Territory.
- (3) Subject to this Act, registration of a declaration of compliance under this section remains in force for the period (not less than 1 year and not more than 5 years) the construction occupations registrar determines, but the registrar may renew the registration from time to time for a period not exceeding 5 years.
 - *Note* A fee may be determined under s 64 (Determination of fees) for this section.

page 16

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

17 Suspension or cancellation of registration of declaration of compliance

- (1) The construction occupations registrar may cancel, or suspend for the period the registrar considers appropriate, the registration of a declaration of compliance if—
 - (a) the registrar is satisfied that an article of electrical equipment to which the declaration relates has been found not to comply with the relevant safety standards in a respect that is likely to be characteristic of articles of the same brand and model; or
 - (b) the approved first seller who lodged the declaration has, in the opinion of the registrar, made, by advertisement or otherwise, representations as to the significance of—
 - (i) the registration of the declaration; or
 - (ii) any mark, stamp or label attached to the article under section 19;

that are intended or likely to mislead any person; or

- (c) the person who lodged the declaration ceases to be an approved first seller; or
- (d) the approved first seller who lodged the declaration so requests in writing.
- (2) If a declaration of compliance is suspended or cancelled under subsection (1), the construction occupations registrar must give written notification of that fact and of the reason for the suspension or cancellation to each regulatory authority for a State or another Territory.
- (3) If a declaration of compliance has been suspended, under subsection (1) the construction occupations registrar may, by written notice given to the approved first seller who lodged the declaration, at any time reduce the period of suspension or rescind the remainder of the suspension.

(4) The construction occupations registrar must rescind the suspension of a declaration of compliance if the registrar is satisfied that the ground for the suspension no longer exists.

18 Transfer of registration of declaration of compliance

- (1) The registration of a declaration of compliance under section 16 may be transferred to the name of another approved first seller in accordance with this section.
- (2) An application for a transfer under this section must be made in writing to the construction occupations registrar, must be signed by the transferor and the transferee and must contain—
 - (a) the names and addresses of the transferor and the transferee; and
 - (b) particulars of the relevant declaration of compliance; and
 - (c) an undertaking on the part of the transferee to comply with the undertakings already specified in that declaration of compliance.
- (3) Subject to subsection (4), the construction occupations registrar must, on receiving an application under subsection (2), transfer the registration of a declaration of compliance by entering the name and address of the transferee in the register referred to in section 21 (1) (c) in relation to that declaration.
 - *Note* A fee may be determined under s 64 (Determination of fees) for this subsection.
- (4) A transfer of the registration of a declaration of compliance must not be made under this section if a transfer of the registration of a declaration of compliance in relation to an article of the same brand and model as the article to which the declaration relates to the same transferee as the transferee referred to in the application under this section has been refused under the corresponding law of a State or another Territory.

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

19 Safety registration mark

- (1) If a declaration of compliance has been registered under this Act, the approved first seller must, from time to time as necessary, ensure that, as soon as practicable, each article of electrical equipment to which the declaration relates that is manufactured or imported by him or her is marked, stamped or labelled as prescribed.
- (2) A person commits an offence if—
 - (a) the person—
 - (i) sells or lets on hire a prescribed article of electrical equipment (a *prescribed article*); or
 - (ii) exposes or advertises for sale or hire a prescribed article; or
 - (iii) installs a prescribed article in, or connects a prescribed article to, an electrical installation; and
 - (b) the prescribed article has not been marked, stamped or labelled in accordance with subsection (1) or a corresponding law of a State or another Territory; and
 - (c) the person is reckless about whether the prescribed article has been marked, stamped or labelled.

Maximum penalty: 200 penalty units.

20

Approved testing laboratories

- (1) If the planning and land authority is satisfied that premises are suitable to be so used, the authority may, on the application of the proprietor of premises, in writing, approve those premises to be used as a testing laboratory for this Act.
- (2) If the planning and land authority is satisfied that those premises are no longer suitable to be used as a testing laboratory for this Act, the authority may, by writing given to the proprietor of those premises,

cancel an approval under subsection (1) in relation to those premises.

- (3) In determining whether premises are suitable to be used as a testing laboratory for this Act, the planning and land authority must have regard to—
 - (a) whether the premises have been approved or refused approval as a testing laboratory under a corresponding law of a State or another Territory; and
 - (b) the facilities at the premises for testing articles of electrical equipment; and
 - (c) any previous record of accuracy or otherwise in the testing of articles of electrical equipment on the premises; and
 - (d) for premises within Australia—whether the premises have been accredited or refused accreditation for the testing of electrical goods by the body known as the National Association of Testing Authorities; and
 - (e) for premises outside Australia—whether the premises have been accredited or refused accreditation by a body or authority with functions at the place where the premises are situated similar to the functions of the body known as the National Association of Testing Authorities; and
 - (f) any other information the authority considers relevant.

21 Registers

- (1) The construction occupations registrar must keep—
 - (a) a register to be called the register of prescribed articles of electrical equipment containing the particulars of each declaration under section 11A and section 11B (and any further information the registrar considers appropriate); and

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

- (b) a register to be called the register of approved first sellers containing—
 - (i) the full name and address of each approved first seller; and
 - (ii) the principal place of business in the ACT of each approved first seller; and
 - (iii) the date of registration of each approved first seller; and
 - (iv) particulars of any cancellations of registration under section 14 (4); and
 - (v) any other particulars that are prescribed; and
- (c) a register to be called the register of declarations of compliance containing, in relation to each declaration of compliance registered under section 16—
 - (i) the full name and address of the declarant; and
 - (ii) a description of the prescribed article of electrical equipment to which the declaration relates; and
 - (iii) a description of the mark, stamp or label applicable to the article in accordance with section 19 (1); and
 - (iv) the date of registration of the declaration; and
 - (v) the period of registration of the declaration and of any renewal of that registration; and
 - (vi) if details of a modification have been given under an undertaking referred to in section 15 (3) (d)—those details; and
 - (vii) particulars of any suspension or cancellation of registration under section 17; and
 - (viii) any further particulars the registrar considers appropriate; and

- (d) a register to be called the register of approved testing laboratories that includes, in relation to each of the premises approved under section 20 as a testing laboratory for this Act—
 - (i) the name and address of the proprietor; and
 - (ii) the address of those premises; and
 - (iii) the date of approval.
- (2) Each register must be available for public inspection during normal working hours and any person may inspect a register and may obtain copies of entries in a register.
 - *Note* A fee may be determined under s 64 (Determination of fees) for this section.

22 Examination and testing of articles

- (1) The construction occupations registrar may, from time to time, examine and test prescribed articles of electrical equipment for the purpose of determining whether or not those articles are safe to use.
- (2) For subsection (1), if a declaration of compliance has been registered under this Act or under the corresponding law of a State or another Territory, the construction occupations registrar may, by written notice given to the approved first seller, require the approved first seller, within the period specified in the notice—
 - (a) to give the registrar a prescribed article of electrical equipment to which the declaration relates; or
 - (b) if it is impracticable to provide such an article, to give the registrar reasonable access to such an article;

and to give the registrar any information in relation to the article specified in the notice.

(3) An approved first seller must comply with a requirement of a notice given to the seller under subsection (2).

Maximum penalty: 200 penalty units.

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

- (4) The construction occupations registrar must ensure that an article provided under subsection (1) is returned to the person who provided it within 2 months after it was provided.
- (5) If an article provided to the construction occupations registrar under subsection (1) is destroyed or damaged while it is in the possession of the registrar (other than destruction or damage that was necessary for the purpose of the examination and testing by the registrar of the article), the person who provided the article is entitled to the amount from the Territory that will reasonably compensate that person for the loss suffered by him or her as a result of that destruction or damage.

Division 3.3 Miscellaneous

23 False representation

A person commits an offence if the person falsely represents that a declaration of compliance is registered under this Act or the corresponding law of a State or another Territory.

Maximum penalty: 200 penalty units.

24 Evidence of registration of declaration of compliance

In any proceedings for an offence against this part, a certificate purporting to be signed by or for the construction occupations registrar or the regulatory authority for a State or another Territory to the effect that at a particular time a declaration of compliance was or was not registered under this Act or the corresponding law of that State or Territory is evidence of the facts stated in the certificate. Section 25

Part 4 Non-prescribed articles of electrical equipment

25 Articles to which pt 4 applies

(1) This part applies to articles of electrical equipment other than—

- (a) a prescribed article of electrical equipment; or
- (b) an article of electrical equipment that is prohibited; or
- (c) an article of electrical equipment used, or for use, in any part of the infrastructure used by an electricity distributor or NERL retailer in connection with the distribution or supply of electricity to premises for consumption.
- (2) In this section:

NERL retailer means a person who holds a retailer authorisation under the *National Energy Retail Law (ACT)*.

26 Minimum safety standards

- (1) A person commits an offence if—
 - (a) the person—
 - (i) sells an article of electrical equipment; or
 - (ii) installs an article of electrical equipment in, or connects an article of electrical equipment to, an electrical installation; and
 - (b) the person is reckless about whether the article complies with the standard.

Maximum penalty: 200 penalty units.

(2) The relevant minimum safety standards for an article of electrical equipment of a particular type are—

R23 06/03/14

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

- (a) the minimum safety requirements for articles of that type under AS/NZS 3820, as in force from time to time; or
- (b) if the regulations provide minimum safety standards for articles of that type—those standards.

27 Offences—energy efficiency requirements for non-prescribed articles of electrical equipment

- (1) A trader commits an offence if—
 - (a) the trader sells an article of electrical equipment; and
 - (b) the article does not comply with the energy efficiency standard prescribed by regulation that applies to the article.

Maximum penalty: 50 penalty units.

- (2) A trader commits an offence if—
 - (a) the trader sells an article of electrical equipment; and
 - (b) the article is not labelled in accordance with a regulation with an energy efficiency label.

Maximum penalty: 10 penalty units.

- (3) A person commits an offence if—
 - (a) the person attaches an energy efficiency label to an article of electrical equipment; and
 - (b) the article does not have the energy efficiency rating indicated by the label.

Maximum penalty: 30 penalty units.

(4) A person commits an offence if the person attaches to an article of electrical equipment anything that falsely appears to be an energy efficiency label.

Maximum penalty: 30 penalty units.

Section 27

- (5) This section does not apply to a second-hand article of electrical equipment.
 - *Note* The defendant has an evidential burden in relation to the matters mentioned in s (5) (see Criminal Code, s 58).
- (6) An offence against this section is a strict liability offence.
- (7) In this section:

energy efficiency label means an energy efficiency label prescribed by regulation.

Examples if regulation made for s 27—applicable law

- 1 The ACT makes a regulation under s 27 about 2 articles of electrical equipment that are not the subject of Ministerial determinations (*GEMS determinations*). The ACT law is the applicable law about those articles.
- 2 The ACT makes a regulation under s 27 about an article of electrical equipment that is the subject of a GEMS determination. The ACT requires '5 star' efficiency for that article, while the GEMS determination provides for '4 star' efficiency. Even though the ACT law appears to be inconsistent with the GEMS determination, the 5 star standard must be met, as the 5 star article would comply simultaneously with both the ACT law and the Commonwealth law.
- Note 1 The Greenhouse and Energy Minimum Standards Act 2012 (Cwlth) (the Commonwealth Act) applies greenhouse and energy minimum standards (GEMS) in association with the supply and commercial use of products that use energy, or affect the energy used by another product. These standards are provided for by requirements in GEMS determinations.

Section 27 only operates if a regulation is made for it, and s 27 and the regulation are consistent with the Commonwealth Act and able to operate concurrently with it (see Self-Government Act, s 28 and Commonwealth Act, s 9).

Note 2 An example is part of the Act, is not exhaustive and may extend, but does not limit, the meaning of the provision in which it appears (see Legislation Act, s 126 and s 132).

R23 06/03/14

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

Part 5

Part 5 Defective articles of electrical equipment

28 Prohibited articles

- (1) The planning and land authority may prepare a notice prohibiting the sale or installation of articles of electrical equipment of a stated class.
- (2) The planning and land authority may act under subsection (1) only if satisfied on reasonable grounds that—
 - (a) articles of the class are, or are likely to become, unsafe to use because of their design or construction; and
 - (b) the use of an article of the class involves, or would involve, a risk of death or injury to a person or damage to property.
- (3) A notice under subsection (1) is a notifiable instrument.

Note A notifiable instrument must be notified under the *Legislation Act 2001*.

(4) The planning and land authority must also publish the notice in a daily newspaper.

29 Sale or installation of prohibited articles

A person commits an offence if-

- (a) the person—
 - (i) sells an article of electrical equipment; or
 - (ii) installs an article in, or connects an article to, an electrical installation; and
- (b) the article is prohibited; and
- (c) the person is reckless about whether the article is prohibited.

Maximum penalty: 200 penalty units.

Section 30

30 Directions about unsafe articles

- (1) This section applies if the planning and land authority believes on reasonable grounds that—
 - (a) a person (the *seller*) has for sale, or may have sold, an article of electrical equipment; and
 - (b) the article is prohibited, does not comply with the relevant standard or is, for any reason, unsafe.
- (2) The planning and land authority may give the seller a direction in writing to do 1 or more of the following:
 - (a) advertise, in a way stated in the direction, warnings approved by the authority about the risks associated with the use of the article;
 - (b) refrain from selling the article;
 - (c) recall an article sold, and—
 - (i) take action stated in the direction to make the article safe and compliant with the relevant standard; or
 - (ii) if it is not practicable to act in accordance with subparagraph (i) or the seller chooses not to take such action—refund to the buyer the purchase price of the article.
- (3) A direction to recall an article may require the seller to give written notice of the recall to people to whom the seller sold, or may have sold, an article to which the direction relates.
- (4) A person must not engage in conduct that contravenes a direction given to the person under this section.

Maximum penalty: 200 penalty units.

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

31 Publication of safety warnings

- (1) The planning and land authority may publish warnings or information to increase public awareness about risks associated with the use of articles of electrical equipment.
- (2) Without limiting the operation of subsection (1), the planning and land authority may publish statements containing advice about the use of—
 - (a) a prohibited article of electrical equipment; or
 - (b) an article of electrical equipment to which a declaration under section 30 (Directions about unsafe articles) applies.
- (3) A person is not personally liable for anything done, or omitted to be done, honestly and without recklessness—
 - (a) in the exercise of a function under this section; or
 - (b) in the reasonable belief that the act was in the exercise of a function under this section.
- (4) Any liability that would, apart from this section, attach to a person attaches instead to the Territory.

Part 6 Serious electrical accidents

Section 32

Part 6 Serious electrical accidents

32 Definitions for pt 6

In this part:

relevant distributor, in relation to a serious electrical accident, means the electricity distributor of the electricity involved in the accident.

serious electrical accident means an accident in which electricity causes, or contributes to—

- (a) the death or injury of a person; or
- (b) damage to property; or
- (c) a fire.

33 Reporting by occupiers and electrical contractors

- (1) An occupier of premises commits an offence if-
 - (a) a serious electrical accident happens at the premises; and
 - (b) the occupier fails to tell the relevant distributor about the accident, by telephone, immediately after the occupier becomes aware of the accident.

Maximum penalty: 50 penalty units.

- (2) An electrical contractor commits an offence if—
 - (a) a serious electrical accident happens in, or in relation to, an electrical installation on which the contractor is carrying out work; and
 - (b) the contractor fails to tell the relevant distributor about the accident, by telephone, immediately after the contractor becomes aware of the accident.

Maximum penalty: 50 penalty units.

page 30

R23 06/03/14

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

- (3) An offence against this section is a strict liability offence.
- (4) This section does not apply if the defendant had reasonable grounds to believe that the relevant distributor had been told about the accident.

34 Reporting by electricity distributor

- (1) An electricity distributor commits an offence if-
 - (a) a serious accident happens—
 - (i) in relation to the distributor's electricity network; or
 - (ii) in the distributor's distribution area; and
 - (b) the distributor fails to tell the construction occupations registrar about the accident, by telephone, immediately after the distributor becomes aware of the accident.

Maximum penalty: 200 penalty units.

- (2) An offence against this section is a strict liability offence.
- (3) This section does not apply if the defendant had reasonable grounds to believe that the construction occupations registrar had been told about the accident.

35 Interference with site of serious electrical accident

(1) A person must not disturb or interfere with the site of a serious electrical accident before it has been inspected by an inspector.

Maximum penalty: 50 penalty units, imprisonment for 6 months or both.

- (2) This section does not apply to anything done—
 - (a) to make the site safe; or
 - (b) by an authorised person; or

Section 36

- (c) except if paragraph (d) applies, more than 24 hours after the accident; or
- (d) if, within 24 hours after the accident, the construction occupations registrar extends the period and tells the person of the extension—after the extended period ends.
- (3) In this section;

authorised person means-

- (a) an inspector; or
- (b) a person acting in accordance with an inspector's directions; or
- (c) a person giving emergency medical assistance to an injured person; or
- (d) a member of the ambulance service, fire and rescue, the rural fire service or the SES.

36 Publication of report of serious electrical accident

- (1) The planning and land authority may publish a report about a serious electrical accident in the interest of public safety.
- (2) A person is not personally liable for anything done, or omitted to be done, honestly and without recklessness—
 - (a) in the exercise of a function under this section; or
 - (b) in the reasonable belief that the act was in the exercise of a function under this section.
- (3) Any liability that would, apart from this section, attach to a person attaches instead to the Territory.

Part 7 Enforcement

Division 7.1 General

37 Definition of *business premises*

In this part:

business premises means premises where a business, trade, profession or calling is carried on, other than a part used for residential purposes.

38 Things connected with offences

- (1) For this part, a thing is *connected with* a particular offence if—
 - (a) the offence has been committed in relation to it; or
 - (b) it will afford evidence of the commission of the offence; or
 - (c) it was used, is being used, or is intended to be used, for the purpose of committing the offence.
- (2) A reference in this part to an *offence* includes an offence that there are reasonable grounds for believing has been, is being, or will be committed.

39 Planning and land authority may require information and documents

- (1) If the planning and land authority is satisfied that a person is capable of providing information or producing a document that the authority reasonably requires for this Act, the authority may, by written notice given to the person, require the person—
 - (a) to give the information to the authority in writing signed by the person or, for a corporation, by an officer of the corporation; or
 - (b) to produce the document to the authority.
- (2) The notice must state—

- (a) the place where the information or document is to be given or produced to the planning and land authority; and
- (b) the time when, or the period within which, the information or document is to be given or produced.
- (3) If a document is produced in accordance with a requirement under subsection (1), the planning and land authority
 - (a) may—
 - (i) take possession of, and may make a copy of, or take extracts from, the document; and
 - (ii) retain possession of the document for the period necessary for this Act; and
 - (b) must, during that period, allow a person who would be entitled to inspect the document, if it was not in the possession of the authority, to inspect the document at any reasonable time.

40 Contravention of requirement by planning and land authority

A person commits an offence if the person engages in conduct that contravenes a requirement made of the person under section 39.

Maximum penalty: 50 penalty units, imprisonment for 6 months or both.

41 Appointment of inspectors

- (1) The construction occupations registrar may appoint a person to be an inspector for this Act.
 - *Note 1* For the making of appointments (including acting appointments), see the Legislation Act, pt 19.3.
 - *Note 2* In particular, an appointment may be made by naming a person or nominating the occupant of a position (see Legislation Act, s 207).

R23 06/03/14

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

- (2) An inspector must exercise his or her functions under this Act in accordance with the conditions of appointment and any direction given to the inspector by the construction occupations registrar.
- (3) A person must not be appointed under subsection (1) unless—
 - (a) the person is an Australian citizen or a permanent resident of Australia; and
 - (b) the construction occupations registrar has certified in writing that, after appropriate inquiry, the registrar is satisfied that the person is a suitable person to be authorised, having regard in particular to—
 - (i) whether the person has any criminal convictions; and
 - (ii) the person's employment record; and
 - (c) the registrar has certified in writing that the registrar is satisfied that the person—
 - (i) has satisfactorily completed adequate training; and
 - (ii) is competent;

to exercise the powers of an inspector proposed to be given to the person.

42 Identity cards

- (1) The construction occupations registrar must give an inspector an identity card stating the person's name and that the person is an inspector.
- (2) The identity card must show—
 - (a) a recent photograph of the person; and
 - (b) the card's date of issue and expiry; and
 - (c) anything else prescribed by regulation.

- (3) A person commits an offence if—
 - (a) the person stops being an inspector; and
 - (b) the person does not return the person's identity card to the construction occupations registrar as soon as practicable, but no later than 7 days after the day the person stops being an inspector.

Maximum penalty: 1 penalty unit.

(4) An offence against this section is a strict liability offence.

Division 7.2 Inspectors' powers

43 General power to enter premises

- (1) For this Act, an inspector may—
 - (a) enter any premises at any time with the consent of the occupier; or
 - (b) enter premises when open to the public; or
 - (c) enter business premises during business hours at the premises; or
 - (d) enter premises in accordance with a warrant under this division.
- (2) An inspector may, without the occupier's consent or a warrant, enter the land around premises to ask the occupier for consent to enter the premises.

44 Production of identity card

An inspector may not remain on premises entered under this part if, on request by the occupier, the inspector does not produce his or her identity card.

45 Consent to entry

- (1) When seeking the consent of an occupier for entering premises under this part an inspector must—
 - (a) produce his or her identity card; and
 - (b) tell the occupier—
 - (i) the purpose of the entry; and
 - (ii) that anything found and seized under this part may be used in evidence in court; and
 - (iii) that consent may be refused.
- (2) If the occupier consents, the inspector must ask the occupier to sign a written acknowledgment—
 - (a) that the occupier was told—
 - (i) the purpose of the entry; and
 - (ii) that anything found and seized under this part may be used in evidence in court; and
 - (iii) that consent may be refused; and
 - (b) that the occupier consented to the entry; and
 - (c) stating the time, and day, when consent was given.
- (3) If the occupier signs an acknowledgment of consent, the inspector must immediately give a copy to the occupier.
- (4) Unless the contrary is proven, a court must presume that an occupier of premises did not consent to an entry to the premises by an inspector under this part if—
 - (a) the question whether the occupier consented to the entry arises in proceedings in the court; and
 - (b) an acknowledgment under this section is not produced in evidence for the entry; and

(c) it is not proved that the occupier consented to the entry.

46 Warrants

- (1) An inspector may apply to a magistrate for a warrant to enter premises.
- (2) The application must be sworn and state the grounds on which the warrant is sought.
- (3) The magistrate may refuse to consider the application until the inspector gives the magistrate all the information the magistrate requires about the application in the way the magistrate requires.
- (4) The magistrate may issue a warrant only if satisfied there are reasonable grounds for suspecting—
 - (a) there is a particular thing or activity (the *evidence*) connected with an offence against this Act; and
 - (b) the evidence is, or may be within the next 14 days, at the premises.
- (5) The warrant must state—
 - (a) that an inspector may, with necessary help and force, enter the premises and exercise the inspector's powers under this part; and
 - (b) the offence for which the warrant is sought; and
 - (c) the evidence that may be seized under the warrant; and
 - (d) the hours when the premises may be entered; and
 - (e) the date, within 14 days after the warrant's issue, the warrant ends.

47 Warrants—application made other than in person

- (1) An inspector may apply for a warrant by phone, fax, radio or other form of communication if the inspector considers it necessary because of—
 - (a) urgent circumstances; or
 - (b) other special circumstances.
- (2) Before applying for the warrant, the inspector must prepare an application stating the grounds on which the warrant is sought.
- (3) The inspector may apply for the warrant before the application is sworn.
- (4) After issuing the warrant, the magistrate must immediately fax a copy to the inspector if it is reasonably practicable to do so.
- (5) If it is not reasonably practicable to fax a copy to the inspector—
 - (a) the magistrate must—
 - (i) tell the inspector what the terms of the warrant are; and
 - (ii) tell the inspector the date and time the warrant was issued; and
 - (b) the inspector must complete a form of warrant (warrant form) and write on it—
 - (i) the magistrate's name; and
 - (ii) the date and time the magistrate issued the warrant; and
 - (iii) the warrant's terms.
- (6) The facsimile warrant, or the warrant form properly completed by the inspector, authorises the entry and the exercise of the inspector's powers under this part.

- (7) The inspector must, at the first reasonable opportunity, send the magistrate—
 - (a) the sworn application; and
 - (b) if the inspector completed a warrant form—the completed warrant form.
- (8) On receiving the documents, the magistrate must attach them to the warrant.
- (9) Unless the contrary is proven, a court must presume that a power exercised by an inspector was not authorised by a warrant under this section if—
 - (a) the question arises in a proceeding before the court whether the exercise of power was authorised by a warrant; and
 - (b) the warrant is not produced in evidence.

48 Powers on entry to premises

- (1) An inspector who enters premises under this part may, for this Act—
 - (a) inspect, measure, photograph or film the premises or anything on the premises; or
 - (b) copy a document on the premises; or
 - (c) test or take samples of or from anything on the premises; or
 - (d) take into the premises any people, equipment or material the inspector reasonably needs for exercising a power under this Act; or
 - (e) require the occupier, or a person on the premises, to give the inspector reasonable help to exercise a power under this Act.

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

- (2) Without limiting the operation of subsection (1), an inspector who enters premises under this part may—
 - (a) check whether an article of electrical equipment or electrical installation on the premises—
 - (i) is safe; or
 - (ii) complies with a relevant standard; or
 - (iii) is prohibited; or
 - (b) check whether electrical wiring work—
 - (i) is safe; or
 - (ii) has been, or is being, done in accordance with this Act.
- (3) A person must take all reasonable steps to comply with a requirement made of the person under subsection (1) (e).

Maximum penalty: 50 penalty units.

(4) An offence against this section is a strict liability offence.

49

- Powers in relation to serious electrical accidents
- (1) This section applies if an inspector believes on reasonable grounds that a serious electrical accident has occurred on premises.
- (2) The inspector may enter the premises at any reasonable time to investigate the accident, ensure the premises are safe and prevent the concealment, loss or destruction of anything reasonably relevant to the investigation.
- (3) The inspector may do anything necessary and reasonable for a purpose mentioned in subsection (2).
- (4) If an inspector acts under this section in the absence of the occupier, the inspector must, when leaving the premises, leave a written notice, secured in a conspicuous place, setting out—
 - (a) the inspector's name; and

- (b) the time and date of the entry; and
- (c) the purpose of the entry; and
- (d) particulars of how to contact the inspector.
- (5) The power to enter premises under this section is additional to the powers under section 43 (General power to enter premises).

50 Powers in relation to unsafe articles of electrical equipment

- (1) This section applies if an inspector believes on reasonable grounds that—
 - (a) a person has an article of electrical equipment for—
 - (i) sale; or
 - (ii) installation in, or connection to, an electrical installation; and
 - (b) the article does not comply with the relevant standard or is unsafe.
- (2) The inspector may give the person a direction in writing to refrain from—
 - (a) selling the article; or
 - (b) installing the article in, or connecting it to, an electrical installation;

unless it is made safe and compliant with the relevant standard.

(3) A person commits an offence if the person engages in conduct that contravenes a direction given to the person under this section.

Maximum penalty: 50 penalty units, imprisonment for 6 months or both.

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

51 Disconnecting etc dangerous electrical equipment and installations

- (1) An inspector who enters premises under this part and finds an article of electrical equipment, or an electrical installation, that the inspector believes on reasonable grounds is a source of danger, may—
 - (a) label the article conspicuously to indicate the danger and prohibit use of the article until it has been repaired or otherwise rendered safe for use; or
 - (b) disconnect the installation.
- (2) A person commits an offence if—
 - (a) an article of electrical equipment labelled under subsection (1) has not been repaired or made safe to use; and
 - (b) the person—
 - (i) uses the article; or
 - (ii) removes or interferes with the label.

Maximum penalty: 50 penalty units, imprisonment for 6 months or both.

52 Power to require name and address

- (1) An inspector may require a person to state the person's name and home or business address if the inspector believes, on reasonable grounds, that the person is committing or has just committed an offence against this Act.
 - *Note* A reference to an Act includes a reference to the statutory instruments made or in force under the Act, including regulations (see Legislation Act, s 104).
- (2) The inspector must tell the person the reason for the requirement and, as soon as practicable, record the reason.

- (3) The person may ask the inspector to produce his or her identity card for inspection by the person.
- (4) A person must comply with a requirement made of the person under subsection (1) if the inspector—
 - (a) tells the person the reason for the requirement; and
 - (b) complies with any request made by the person under subsection (3).

Maximum penalty: 10 penalty units.

(5) An offence against this section is a strict liability offence.

53 Power to seize evidence

- (1) An inspector who enters premises with a warrant under this part may seize the evidence for which the warrant was issued.
- (2) An inspector who enters premises under this part with the consent of the occupier may seize a thing on the premises if—
 - (a) the inspector is satisfied the thing is connected with an offence against this Act; and
 - (b) seizure of the thing is consistent with the purpose of the entry as told to the occupier in seeking the occupier's consent.
- (3) An inspector may also seize another thing on premises entered under this part if the inspector is satisfied—
 - (a) the thing is connected with an offence against this Act; and
 - (b) the seizure is necessary to prevent the thing being—
 - (i) concealed, lost or destroyed; or
 - (ii) used to commit, continue or repeat the offence.

- (4) Having seized a thing, an inspector may—
 - (a) remove the thing from the premises where it was seized (the *place of seizure*) to another place; or
 - (b) leave the thing at the place of seizure but restrict access to it.
- (5) A person commits an offence if—
 - (a) the person interferes with a thing to which access has been restricted under subsection (4); or
 - (b) the person does not have the construction occupations registrar's approval to interfere with the thing.

Maximum penalty: 50 penalty units, imprisonment for 6 months or both.

54 Receipt for things seized

- (1) As soon as practicable after a thing is seized by an inspector under this part, the inspector must give a receipt for it to the person from whom it was seized.
- (2) If, for any reason, it is not practicable to comply with subsection (1), the inspector must leave the receipt, secured conspicuously at the place of seizure.

55 Access to things seized

A person who would, apart from the seizure, be entitled to a thing seized under this part may—

- (a) inspect it; and
- (b) if it is a document—take extracts from it or make copies of it.

56 Return of things seized

- (1) A thing seized under this part must be returned to its owner, or reasonable compensation must be paid to the owner by the Territory for the loss of the thing, if—
 - (a) a prosecution for an offence relating to the thing is not instituted within 90 days of the seizure; or
 - (b) the court does not find the offence proved in a prosecution for an offence relating to the thing.
- (2) A thing seized under this part is forfeited to the Territory if a court—
 - (a) finds an offence relating to the thing to be proved; and
 - (b) orders the forfeiture.
- (3) If subsection (2) (a) applies, but a court does not order forfeiture of the thing seized, the construction occupations registrar must return the thing to its owner or the Territory must pay reasonable compensation to the owner for the loss of the thing.

57 Power to inspect electrical wiring work

- (1) An inspector may enter and remain on premises to conduct a test or inspection required under part 2 (Electrical wiring work and electrical installations) in relation to an electrical installation or electrical wiring work.
- (2) An inspector may enter and remain on the premises under subsection (1)—
 - (a) at any reasonable time; and
 - (b) with the people, equipment or material that the inspector reasonably needs to conduct the test or inspection.

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

- (3) However, the inspector may not, under this section—
 - (a) enter or remain on premises if, on request by the occupier, the inspector does not produce his or her identity card; or
 - (b) without the consent of the occupier, enter or remain on any part of the premises used for residential purposes.
- (4) The power to enter premises under this section is additional to the powers under section 43 (General power to enter premises).

Division 7.3 Miscellaneous

58 Self-incrimination etc

- (1) A person is not excused from providing information or producing a document when required to do so under this part on the ground that the information or document might tend to incriminate the person.
- (2) However-
 - (a) the provision of the information or document; or
 - (b) any information, document or thing obtained as a direct or indirect consequence of providing the information or document;

is not admissible in evidence against the person in criminal proceedings.

- (3) Subsection (2) does not apply to proceedings for—
 - (a) an offence against this part; or
 - (b) any other offence in relation to the falsity of the information or document.
 - *Note 1* A reference to an offence against a Territory law includes a reference to a related ancillary offence, eg attempt (see *Legislation Act 2001*, s 189).
 - *Note 2* The *Legislation Act 2001*, s 171 deals with the application of client legal privilege.

59 Damage etc to be minimised

- (1) In the exercise, or purported exercise, of a function under this part, an inspector must take all reasonable steps to ensure that he or she, and any person assisting the inspector, causes as little inconvenience, detriment and damage as is practicable.
- (2) If an inspector, or a person assisting an inspector, damages anything in the exercise or purported exercise of a function under this part, the inspector must give written notice of the particulars of the damage to the person whom the inspector believes on reasonable grounds is the owner of the thing.
- (3) If the damage occurs on premises entered under this part in the absence of the occupier, the notice may be given by securing it in a conspicuous place on the premises.

60 Compensation

- (1) A person may claim reasonable compensation from the Territory if the person suffers loss or expense because of the exercise, or purported exercise, of a function under this part by an inspector or a person assisting an inspector.
- (2) Compensation may be claimed and ordered in a proceeding for—
 - (a) compensation brought in a court of competent jurisdiction; or
 - (b) an offence against this Act brought against the person making the claim for compensation.
- (3) A court may order the payment of reasonable compensation for the loss or expense only if it is satisfied it is just to make the order in the circumstances of the particular case.
- (4) The regulations may prescribe matters that may, must or must not be taken into account by the court in considering whether it is just to make the order.

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

Part 8 Notification and review of decisions

61 Meaning of *reviewable decision*—pt 8

In this part:

reviewable decision means a decision mentioned in schedule 1, column 3 under a provision of this Act mentioned in column 2 in relation to the decision.

62 Reviewable decision notices

If a person makes a reviewable decision, the person must give a reviewable decision notice to each entity mentioned in schedule 1, column 4 in relation to the decision.

- *Note 1* The person must also take reasonable steps to give a reviewable decision notice to any other person whose interests are affected by the decision (see *ACT Civil and Administrative Tribunal Act 2008*, s 67A).
- *Note 2* The requirements for reviewable decision notices are prescribed under the *ACT Civil and Administrative Tribunal Act 2008*.

62A Applications for review

The following may apply to the ACAT for review of a reviewable decision:

- (a) an entity mentioned in schedule 1, column 4 in relation to the decision;
- (b) any other person whose interests are affected by the decision.
- *Note* If a form is approved under the *ACT Civil and Administrative Tribunal Act 2008* for the application, the form must be used.

Part 9 Miscellaneous

Section 63

Part 9 Miscellaneous

63 Evidence

- (1) The construction occupations registrar may, by signed writing, certify—
 - (a) that a document attached to the certificate is a true copy of AS/NZS 3000, as in force at a stated date; and
 - (b) whether the standard is still in force and, if not, the period during which the standard was in force.
- (2) The registrar may, by signed writing, certify that a person was or was not on a date or dates or during a period specified in the certificate the holder of a specified licence or permit.
- (3) A document that purports to be a certificate under subsection (1) or (2) is presumed, unless the contrary is proved, to be such a certificate and to have been duly given.
- (4) A certificate under subsection (1) is evidence of the matters specified in it and of the determination a copy of which is attached to it.
- (5) A certificate under subsection (2) is evidence of the matters specified in it.
- (6) A document that purports to be a signed on behalf of a prescribed authority in a State or another Territory and states that a specified class, description or type of article of electrical equipment was or was not on a specified date approved by that authority is evidence of the matters stated in the document.

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

64 Determination of fees

- (1) The Minister may determine fees for this Act.
 - *Note* The *Legislation Act 2001* contains provisions about the making of determinations and regulations relating to fees (see pt 6.3).
- (2) A determination is a disallowable instrument.
 - *Note* A disallowable instrument must be notified, and presented to the Legislative Assembly, under the *Legislation Act 2001*.

65 Approved forms

- (1) The construction occupations registrar may approve forms for this Act.
- (2) If the construction occupations registrar approves a form for a particular purpose, the approved form must be used for that purpose.

Note For other provisions about forms, see the Legislation Act, s 255.

(3) An approved form is a notifiable instrument.

Note A notifiable instrument must be notified under the *Legislation Act 2001*.

66 Regulation-making power

- (1) The Executive may make regulations for this Act.
 - *Note* Regulations must be notified, and presented to the Legislative Assembly, under the *Legislation Act 2001*.
- (2) A regulation may make provision in relation to energy for articles of electrical equipment, including the following:
 - (a) standards of energy efficiency;
 - (b) examination and testing;
 - (c) labels and labelling.
- (3) A regulation may apply, adopt or incorporate the law of another jurisdiction or an instrument as in force from time to time.

Part 9 Miscellaneous

Section 66

- (4) The Legislation Act, section 47 (5) or (6) does not apply in relation to the law of another jurisdiction or an instrument applied, adopted or incorporated under a regulation.
 - *Note* Laws of another jurisdiction and instruments mentioned in s (4) do not need to be notified under the Legislation Act because s 47 (5) and (6) do not apply (see Legislation Act, s 47 (7)).
- (5) A regulation may create offences and fix maximum penalties of not more than 60 penalty units for the offences.
- (6) In this section:

law	of	another	jurisdiction—see	the	Legislation	Act,
sectio	n 47	(10).				

page 52

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14

Schedule 1 Reviewable decisions

(see pt 8)

column 1 item	column 2 section	column 3 decision	column 4 entity
1	11A (1)	declare article of electrical equipment is prescribed article of electrical equipment	entity that has interests affected by declaration
2	11A (3)	state safety standard that article of electrical equipment must comply with	entity that has interests affected by safety standard
3	14 (3)	refuse to register person as approved first seller	applicant for approval
4	14 (4)	cancel registration of approved first seller	entity that has approval cancelled
5	16 (1)	refuse to register declaration of compliance	entity that lodged declaration
6	16 (3)	determine period of registration of declaration of compliance	entity that lodged declaration
7	17 (1)	cancel or suspend registration of declaration of compliance	entity that has registration cancelled or suspended

Schedule 1 Reviewable decisions

column 1 item	column 2 section	column 3 decision	column 4 entity
8	17 (3)	refuse to reduce period of suspension or cancel remainder of suspension	entity that has registration suspended or cancelled
9	20 (1)	refuse to approve premises as testing laboratory	applicant for approval
10	20 (2)	cancel approval of premises as testing laboratory	entity that has approval cancelled
11	22 (2)	impose requirement on approved first seller	entity on which requirement imposed
12	28	prohibit sale or installation of articles of electrical equipment of stated class	entity that has interests affected by prohibition

page 54

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14

Dictionary

(see s 3)

- *Note 1* The Legislation Act contains definitions and other provisions relevant to this Act.
- *Note 2* For example, the Legislation Act, dict, pt 1, defines the following terms:
 - ACAT
 - Australian citizen
 - bankrupt or personally insolvent
 - daily newspaper
 - function
 - home address
 - planning and land authority
 - reviewable decision notice
 - State
 - under.

approved first seller, for part 3 (Prescribed articles of electrical equipment)—see section 9.

article of electrical equipment means-

- (a) a wire, cable, fitting, meter, insulator, switchboard, or apparatus designed or intended for use in an electrical installation; or
- (b) an appliance, fitting or apparatus operated by electricity and the cable and other things required for its connection to an electrical installation.

AS/NZS 3000 means Australian/New Zealand Standard 3000 (Wiring Rules) as in force from time to time.

AS/NZS 3017 means Australian/New Zealand Standard 3017 (Electrical installations—testing and inspection guidelines) as in force from time to time.

AS/NZS 3820 means Australian/New Zealand Standards 3820 (Essential safety requirements for low voltage electrical equipment) as in force from time to time.

business premises, for part 7 (Enforcement)—see section 37.

connected with, for part 7 (Enforcement)—see section 38 (1).

corresponding law, for part 3 (Prescribed articles of electrical equipment)—see section 9.

declaration of compliance, for part 3 (Prescribed articles of electrical equipment)—see section 9.

electrical installation—

- (a) means electrical wiring or cable used or for use in carrying or controlling electricity (other than electricity with a voltage of not more than 50V a.c. or 120V ripple-free d.c.), including the following:
 - (i) a wiring system, switchgear, control gear, generator, electrical accessory, electrical appliance, or fitting, that is used or for use in the conversion, storage, transmission, distribution, generation or use of electrical energy and connected to wiring or cable;
 - (ii) a switch, fuse, plug, socket outlet, lighting outlet, adaptor, ceiling rose or other device associated with wiring, a switchboard, or an appliance, mentioned in subparagraph (i);
 - (iii) a consuming device in which electricity is converted into heat, motion or another form of energy, or is substantially changed in its electrical character;
 - (iv) support for electrical wiring or cable; but
- (b) does not include—
 - (i) a portable generator or storage device supplying, or for the supply of, electricity to the installation; or

page 56

R23 06/03/14

- (ii) an appliance that receives, or is intended to receive, its main electricity supply through a socket connection; or
- (iii) a lamp; or
- (iv) an electricity network or part of a network; or
- (v) telecommunications cabling or equipment that operates or is intended to operate at a voltage of 90V a.c. or lower.

electrical wiring work—

- (a) means the installation, replacement, augmentation, curtailing, maintenance, repair, or alteration of the location of all or part of, an electrical installation, other than—
 - (i) an electrical installation that operates at extra low voltage; or
 - (ii) telecommunications cabling or equipment that operates at a voltage not greater than 90V a.c.; but
- (b) does not include—
 - (i) plugging a plug into a socket outlet, or unplugging it; or
 - (ii) fitting a lamp to a lighting outlet or removing it; or
 - (iii) fitting, removing or replacing a fuse or fuse wire if the fuse or wire cannot sustainedly conduct more than 30A.

electricity distributor—see the Utilities Act 2000, dictionary.

electricity network—see the *Utilities Act 2000*, section 7 (Electricity network).

engage in conduct means—

- (a) do an act; or
- (b) omit to do an act.

generator includes a generator that generates electricity from any energy source.

Examples—energy source

- 1 the sun
- 2 diesel fuel
- 3 gas
- 4 wind
- *Note* An example is part of the Act, is not exhaustive and may extend, but does not limit, the meaning of the provision in which it appears (see Legislation Act, s 126 and s 132).

inspector means a person appointed as an inspector under section 41.

occupier, of premises, includes—

- (a) a person believed on reasonable grounds to be an occupier of the premises; and
- (b) a person apparently in charge of the premises.

offence, for part 7 (Enforcement)—see section 38 (2).

premises means a building, structure or place (whether built on or not and whether enclosed or not), and includes an aircraft, a vessel and a vehicle.

prescribed article of electrical equipment—see section 11.

prohibited, in relation to an article of electrical equipment, means an article that is prohibited under section 28 (1).

regulatory authority, for a State, means-

- (a) an entity that carries out functions similar to the functions that the construction occupations registrar carries out under part 3 (Prescribed articles of electrical equipment) under a law of the State that corresponds, or substantially corresponds, to that part; or
- (b) an entity prescribed by regulation.

page 58

R23 06/03/14

relevant distributor, for part 6 (Serious electrical accidents)—see section 32.

relevant safety standard, for part 3 (Prescribed articles of electrical equipment)—see section 9.

relevant standard—

- (a) for a prescribed article of electrical equipment—means a relevant safety standard under part 3 (see s 9); and
- (b) for an article of electrical equipment to which part 4 (Non-prescribed articles of electrical equipment) applies—see section 26 (Minimum safety standards).

reviewable decision, for part 8 (Notification and review of decisions)—see section 61.

sell includes-

- (a) barter or exchange; and
- (b) let on hire; and
- (c) offer, expose or advertise for sale, barter, exchange or letting on hire.

serious electrical accident, for part 6 (Serious electrical accidents)—see section 32.

About the endnotes

Endnotes

2

1

About the endnotes

Amending and modifying laws are annotated in the legislation history and the amendment history. Current modifications are not included in the republished law but are set out in the endnotes.

Not all editorial amendments made under the *Legislation Act 2001*, part 11.3 are annotated in the amendment history. Full details of any amendments can be obtained from the Parliamentary Counsel's Office.

Uncommenced amending laws are not included in the republished law. The details of these laws are underlined in the legislation history. Uncommenced expiries are underlined in the legislation history and amendment history.

If all the provisions of the law have been renumbered, a table of renumbered provisions gives details of previous and current numbering.

The endnotes also include a table of earlier republications.

-	
A = Act	NI = Notifiable instrument
AF = Approved form	o = order
am = amended	om = omitted/repealed
amdt = amendment	ord = ordinance
AR = Assembly resolution	orig = original
ch = chapter	par = paragraph/subparagraph
CN = Commencement notice	pres = present
def = definition	prev = previous
DI = Disallowable instrument	(prev) = previously
dict = dictionary	pt = part
disallowed = disallowed by the Legislative	r = rule/subrule
Assembly	reloc = relocated
div = division	renum = renumbered
exp = expires/expired	R[X] = Republication No
Gaz = gazette	RI = reissue
hdg = heading	s = section/subsection
IA = Interpretation Act 1967	sch = schedule
ins = inserted/added	sdiv = subdivision
LA = Legislation Act 2001	SL = Subordinate law
LR = legislation register	sub = substituted
LRA = Legislation (Republication) Act 1996	underlining = whole or part not commenced
mod = modified/modification	or to be expired

Abbreviation key

page 60

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

¹

3 Legislation history

This Act was originally a Commonwealth ordinance—the *Electricity Ordinance 1971* No 30 (Cwlth).

The *Australian Capital Territory (Self-Government) Act 1988* (Cwlth), s 34 (4) converted most former Commonwealth ordinances in force in the ACT into ACT enactments. This allowed the ACT Legislative Assembly to amend and repeal the laws. This Act was converted into an ACT enactment on 11 May 1989 (self-government day).

As with most ordinances in force in the ACT, the name was changed from *Ordinance* to *Act* by the *Self-Government (Citation of Laws) Act 1989* A1989-21, s 5 on 11 May 1989 (self-government day).

The Act was renamed as the *Electricity Safety Act 1971* by the *Utilities* (*Consequential Provisions*) *Act 2000* A2000-66 (see sch 1 pt 4).

Before 11 May 1989, ordinances commenced on their notification day unless otherwise stated (see *Seat of Government (Administration) Act 1910* (Cwlth), s 12).

After 11 May 1989 and before 10 November 1999, Acts commenced on their notification day unless otherwise stated (see *Australian Capital Territory* (*Self-Government*) *Act 1988* (Cwlth) s 25).

Legislation before becoming Territory enactment

Electricity Safety Act 1971 A1971-30

notified 2 December 1971 commenced 1 January 1972

as amended by

Electricity Ordinance 1972 Ord1972-27

notified 4 August 1972 commenced 4 August 1972

Ordinances Revision Ordinance 1977 Ord1977-65 sch 2

notified 22 December 1977 commenced 22 December 1977

Ordinances Revision Ordinance 1978 Ord1978-46 sch 2

notified 28 December 1978 commenced 28 December 1978

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 61

3	Legislation	history
---	-------------	---------

Electricity (Amendment) Ordinance 1982 Ord1982-61

notified 18 August 1982 commenced 18 August 1982

Electricity (Amendment) Ordinance 1985 Ord1985-20

notified 30 May 1985 commenced 30 June 1985 (see Cwlth Gaz 1985 No S242)

Magistrates Court Ordinance 1985 Ord1985-67 sch pt 1

notified 19 December 1985 commenced 1 February 1986 (s 2 and Cwlth Gaz 1986 No G3)

Electricity (Amendment) Ordinance 1987 Ord1987-5

notified 24 February 1987 commenced 24 February 1987

Electricity and Water (Consequential Amendments) Ordinance 1988 Ord1988-31 sch

notified 30 June 1988 commenced 1 July 1988 (s 2)

Self-Government (Consequential Amendments) Ordinance 1989 Ord1989-38 sch 1

notified 10 May 1989 (Cwlth Gaz 1989 No S160) s 1, s 2 commenced 10 May 1989 (s 2 (1)) sch 1 commenced 11 May 1989 (s 2 (2) and see Cwlth Gaz 1989 No S164)

Legislation after becoming Territory enactment

Royal Commissions and Inquiries (Consequential Provisions) Act 1991 A1991-3 sch

notified 1 March 1991 (Gaz 1991 No S7) s 1, s 2 commenced 1 March 1991 (s 2 (1)) sch commenced 1 May 1991 (s 2 (2) and see Gaz 1991 No 16)

Electricity (Amendment) Act 1994 A1994-52

notified 5 October 1994 s 1, s 2 commenced 5 October 1994 remainder commenced 5 October 1994 (see Gaz 1994 No S207)

page 62

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

Administrative Appeals (Consequential Amendments) Act 1994 A1994-60 sch 1

notified 11 October 1994 (Gaz 1994 No S197) s 1, s 2 commenced 11 October 1994 (s 2 (1)) sch 1 commenced 14 November 1994 (s 2 (2) and see Gaz 1994 No S250)

Statute Law Revision (Penalties) Act 1994 A1994-81 sch

notified 29 November 1994 (Gaz 1994 No S253) s 1, s 2 commenced 29 November 1994 (s 2 (1)) sch commenced 29 November 1994 (s 2 (2) and Gaz 1994 No S269)

as modified by

Electricity and Water (Modification) Regulations SL1995-24

notified 30 June 1995 commenced 1 July 1995

as amended by

Statute Law Revision Act 1995 A1995-46 sch

notified 18 December 1995 (Gaz 1995 No S306) amdts commenced 18 December 1995 (s 2)

Electricity (Miscellaneous Provisions) Act 1996 A1996-28

notified 1 July 1996 commenced 1 July 1996

Remuneration Tribunal (Consequential Amendments) Act 1997 A1997-41 sch 1 (as am by A2002-49 amdt 3.222)

notified 19 September 1997 (Gaz 1997 No S264) commenced 24 September 1997 (s 2 as am by A2002-49 amdt 3.222)

Legal Practitioners (Consequential Amendments) Act 1997 A1997-96 sch 1

notified 1 December 1997 (Gaz 1997 No S380) s 1, s 2 commenced 1 December 1997 (s 2 (1)) sch 1 commenced 1 June 1998 (s 2 (2))

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 63

3	Legislation	history
---	-------------	---------

Electricity (Amendment) Act 1998 A1998-51

notified 16 November 1998 (Gaz 1998 No S205) ss 1-3 commenced 16 November 1998 (s 2 (1)) remainder 14 April 1999 (s 2 (2) and Gaz 1999 No 15)

Statute Law Revision (Penalties) Act 1998 A1998-54 sch

notified 27 November 1998 (Gaz 1998 No S207) s 1, s 2 commenced 27 November 1998 (s 2 (1)) sch commenced 9 December 1998 (s 2 (2) and Gaz 1998 No 49)

Electricity (Amendment) Act 1999 A1999-53

notified 17 September 1999 (Gaz 1999 No S54) commenced 17 September 1999 (s 2)

Utilities (Consequential Provisions) Act 2000 A2000-66 sch 1 pt 4

notified 20 December 2000 (Gaz 2000 No S68) s 1, s 2 commenced 20 December 2000 (IA s 10B) sch 1 pt 4 commenced 1 January 2001 (Gaz 2000 No S69)

Electricity Amendment Act 2000 A2000-69

notified 20 December 2000 (Gaz 2000 No S68) commenced 20 December 2000 (s 2)

Legislation (Consequential Amendments) Act 2001 A2001-44 pt 122

notified 26 July 2001 (Gaz 2001 No 30) s 1, s 2 commenced 26 July 2001 (IA s 10B) pt 122 commenced 12 September 2001 (s 2 and see Gaz 2001 No S65)

Legislation Amendment Act 2002 A2002-11 pt 2.18

notified LR 27 May 2002 s 1, s 2 commenced 27 May 2002 (LA s 75) pt 2.18 commenced 28 May 2002 (s 2 (1))

Criminal Code 2002 A2002-51 pt 1.8

notified LR 20 December 2002 s 1, s 2 commenced 20 December 2002 (LA s 75 (1)) pt 1.8 commenced 1 January 2003 (s 2 (1))

page 64

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

Statute Law Amendment Act 2002 (No 2) A2002-49 amdt 3.222 notified LR 20 December 2002

s 1, s 2 taken to have commenced 7 October 1994 (LA s 75 (2))

amdt 3.222 commenced 24 September 1997 (s 2 (3)) Note This Act only amends the Remuneration Tribunal

(Consequential Amendments) Act 1997 A1997-41.

Vocational Education and Training Act 2003 A2003-37 sch 2 pt 2.3

notified LR 8 September 2003

s 1, s 2 commenced 8 September 2003 (LA s 75 (1))

sch 2 pt 2.3 commenced 1 November 2003 (s 2)

Construction Occupations Legislation Amendment Act 2004 A2004-13 sch 2 pt 2.9

notified LR 26 March 2004

s 1, s 2 commenced 26 March 2004 (LA s 75 (1)) sch 2 pt 2.9 commenced 1 September 2004 (s 2 and see Construction Occupations (Licensing) Act 2004 A2004-12, s 2 and CN2004-8)

Criminal Code (Theft, Fraud, Bribery and Related Offences) Amendment Act 2004 A2004-15 sch 1 pt 1.12, sch 2 pt 2.32

notified LR 26 March 2004 s 1, s 2 commenced 26 March 2004 (LA s 75 (1)) sch 1 pt 1.12, sch 2 pt 2.32 commenced 9 April 2004 (s 2 (1))

Criminal Code Harmonisation Act 2005 A2005-54 sch 1 pt 1.19

notified LR 27 October 2005

s 1, s 2 commenced 27 October 2005 (LA s 75 (1)) sch 1 pt 1.19 commenced 24 November 2005 (s 2)

Construction Occupations Legislation Amendment Act 2006 A2006-15 sch 1 pt 1.4

notified LR 6 April 2006 s 1, s 2 commenced 6 April 2006 (LA s 75 (1)) sch 1 pt 1.4 commenced 1 September 2006 (s 2 and CN2006-19)

Statute Law Amendment Act 2007 (No 3) A2007-39 sch 3 pt 3.12

notified LR 6 December 2007

s 1, s 2 commenced 6 December 2007 (LA s 75 (1))

sch 3 pt 3.12 commenced 27 December 2007 (s 2)

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 65

3 Legislation history

ACT Civil and Administrative Tribunal Legislation Amendment Act 2008 (No 2) A2008-37 sch 1 pt 1.37

notified LR 4 September 2008

s 1, s 2 commenced 4 September 2008 (LA s 75 (1)) sch 1 pt 1.37 commenced 2 February 2009 (s 2 (1) and see ACT Civil and Administrative Tribunal Act 2008 A2008-35, s 2 (1) and CN2009-2)

Statute Law Amendment Act 2009 A2009-20 sch 3 pt 3.26

notified LR 1 September 2009 s 1, s 2 commenced 1 September 2009 (LA s 75 (1)) sch 3 pt 3.26 commenced 22 September 2009 (s 2)

Statute Law Amendment Act 2009 (No 2) A2009-49 sch 3 pt 3.24

notified LR 26 November 2009 s 1, s 2 commenced 26 November 2009 (LA s 75 (1)) sch 3 pt 3.24 commenced 17 December 2009 (s 2)

Planning and Building Legislation Amendment Act 2011 A2011-23 pt 4

notified LR 6 July 2011 pt 1 commenced 6 July 2011 (s 2 (1)) pt 4 commenced 7 July 2011 (s 2 (5))

Statute Law Amendment Act 2012 A2012-21 sch 3 pt 3.16

notified LR 22 May 2012 s 1, s 2 commenced 22 May 2012 (LA s 75 (1)) amdt 3.65 commenced 5 June 2012 (s 2 (2)) sch 3 pt 3.16 remainder commenced 5 June 2012 (s 2 (1))

National Energy Retail Law (Consequential Amendments) Act 2012 A2012-32 pt 7

notified LR 14 June 2012 s 1, s 2 commenced 14 June 2012 (LA s 75 (1)) pt 7 commenced 1 July 2012 (s 2 (1) and see National Energy Retail Law (ACT) Act 2012 A2012-31, s 2 (1) and CN2012-12)

Construction and Energy Efficiency Legislation Amendment Act 2013 A2013-31 pt 8

notified LR 26 August 2013

s 1, s 2 commenced 26 August 2013 (LA s 75 (1)) pt 8 commenced 27 August 2013 (s 2 (3))

page 66

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

Legislation history 3

Construction and Energy Efficiency Legislation Amendment Act 2014 A2014-2 pt 5

notified LR 5 March 2014

- s 1, s 2 commenced 5 March 2014 (LA s 75 (1))
- pt 5 commenced 6 March 2014 (s 2)

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 67

4	Amendment history	V
---	-------------------	---

4 Amendment history

	5
Title title	sub A2000-66 sch 1 pt 4
Name of Act s 1	sub A2000-66 sch 1 pt 4
Dictionary	
s 2	am A1994-52 sch
• =	om A2001-44 amdt 1.1403
	ins A2004-13 amdt 2.22
Notes	
s 3 hdg	sub A2000-69 s 4
s 3	orig s 3 om Ord1977-65 sch 2
	(prev s 4) renum as s 3 A1994-52 s 48
	am A1994-52 s 4, sch
	sub A2004-13 amdt 2.23; A2005-54 amdt 1.111
	def administrative appeals tribunal ins A1994-52 s 4
	om A1995-46 sch
	def <i>authority</i> ins Ord1988-31 sch
	om A2000-69 s 4
	def board ins A1994-52 s 4
	om A2004-13 amdt 2.23
	def <i>chairperson</i> ins A1994-52 s 4
	om A2004-13 amdt 2.23
	def chief executive officer ins Ord1988-31 sch
	om A2000-69 s 4
	def <i>company</i> ins A1996-28 s 4
	om A2000-69 s 4
	def <i>deputy chairperson</i> ins A1994-52 s 4
	om A2004-13 amdt 2.23
	def <i>determined fee</i> ins A1994-52 s 4
	om A2001-44 amdt 1.1404
	def <i>electrical installation</i> am A1999-53 s 4
	sub A2000-66 sch 1 pt 4
	om A2004-13 amdt 2.23
	def electrical wiring work am A1995-52 s 4
	sub A1999-53 s 4
	om A2004-13 amdt 2.23
	def <i>electrician's licence, grade B</i> sub A2000-69 s 4 om A2004-13 amdt 2.23
	def <i>Electricity and Water Act</i> sub A2000-69 s 4
	def Electricity and Water Ordinance ins Ord1988-31
	sch
	om A2004-13 amdt 2.23

page 68

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

Amendment history 4

def electricity distributor ins A2000-69 s 4 sub A2000-66 sch 1 pt 4 om A2004-13 amdt 2.23 def electricity network ins A2000-66 sch 1 pt 4 om A2004-13 amdt 2.23 def extra low voltage ins A1994-52 s 4 om A2004-13 amdt 2.23 def function ins A2000-69 s 4 om A2004-13 amdt 2.23 def incidental electrical work ins A1994-52 s 4 om A2004-13 amdt 2.23 def inspector ins A2000-69 s 4 om A2004-13 amdt 2.23 def licence sub A2000-69 s 4 om A2004-13 amdt 2.23 def *member* ins A1994-52 s 4 om A2004-13 amdt 2.23 def Mutual Recognition Act ins A1994-52 s 4 om A2004-13 amdt 2.23 def occupier ins A2000-69 s 4 om A2004-13 amdt 2.23 def *permit* ins A1994-52 s 4 om A2004-13 amdt 2.23 def premises ins A2000-69 s 4 om A2004-13 amdt 2.23 def prescribed article of electrical equipment ins A2000-69 s 4 om A2004-13 amdt 2.23 def prohibited ins A2000-69 s 4 om A2004-13 amdt 2.23 def Register ins A1994-52 s 4 om A2004-13 amdt 2.23 def registrar ins A1994-52 s 4 sub A2000-69 s 4 om A2004-13 amdt 2.23 def regulatory authority ins A1994-52 s 4 sub A2000-69 s 4 om A2004-13 amdt 2.23 def relevant standard ins A2000-69 s 4 am A2001-44 amdt 1.1405 om A2004-13 amdt 2.23 def restricted electrical licence ins A1994-52 s 4 om A2004-13 amdt 2.23 def sell ins A2000-69 s 4 om A2004-13 amdt 2.23 def serious electrical accident ins A2000-69 s 4 om A2004-13 amdt 2.23 def the Act om Ord1988-31 sch

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 69

4 Amendment history

def the Authority om Ord1988-31 sch def the Chairman om Ord1988-31 sch def the Registrar om A1995-52 s 4 def wireman's licence om A1995-52 s 4 Offences against Act—application of Criminal Code etc s 3A ins A2005-54 amdt 1.111 The Electrical Licensing Board renum as pt 2 hdg pt 1A hdg Electrical wiring work and electrical installations pt 2 hdg orig pt 2 hdg renum as pt 3 hdg prev pt 2 hdg (prev pt 1A hdg) ins A1994-52 s 6 renum as pt 2 hdg A1994-52 s 48 om A2004-13 amdt 2.24 pres pt 2 hdg (prev pt 3 hdg) renum as pt 4 hdg A1994-52 s 48 renum as pt 2 hdg R10 LA (see A2004-13 amdt 2.43) am A2014-2 s 22 Connecting electrical installations to network-inspections orig s 4 renum as s 3 s 4 (prev s 5) sub A1994-52 s 5 renum as s 4 A1994-52 s 48 om A2004-13 amdt 2.24 pres s 4 (prev s 14) am A1994-52 sch renum as s 33 A1994-52 s 48 am A1994-81 sch mod SL1995-24 reg 3 sub A1996-28 s 5 am A1998-51 s 4 sub A2000-69 s 8; A2000-66 sch 1 pt 4 renum as s 32 R4 LA (see A2000-69 s 29) renum as s 4 R10 LA (see A2004-13 amdt 2.43) sub A2005-54 amdt 1.112 Compliance with AS/NZS 3000 s 5 orig s 5 renum as s 4 (prev s 5A) ins A1994-52 s 6 renum as s 5 A1994-52 s 48 am A2000-69 s 5; A2001-44 amdts 1.1406-1.1410 om A2004-13 amdt 2.24 pres s 5 (prev s 33A) ins A1998-51 s 5 renum as s 33 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.26 renum as s 5 R10 LA (see A2004-13 amdt 2.43) sub A2005-54 amdt 1.112

page 70

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

Amendment history 4

Constitution of board s 5A renum as s 5 Chairperson and deputy chairperson of board s 5B renum as s 6 Term of office s 5C renum as s 7 Resignation s 5D renum as s 8 Functions of board renum as s 9 s 5E Powers of board s 5F renum as s 10 Delegation s 5G renum as s 11 **Recommendations to Minister** s 5H renum as s 12 **Deputies** renum as s 13 s 5J **Remuneration and allowances** s 5K renum as s 14 Staff s 5L renum as s 15 and then s 14 Meetings of board renum as s 16 and then s 15 s 5M Quorum s 5N renum as s 17 and then s 16 Voting s 5P renum as s 18 and then s 17 Board may determine procedure s 5Q renum as s 19 and then s 18 Courses, examinations etc s 5R renum as s 20 and then s 19 Testing and reporting of electrical work orig s 6 renum as s 21 and then s 20 s 6 (prev s 5B) ins A1994-52 s 6 renum as s 6 A1994-52 s 48 om A2004-13 amdt 2.24 pres s 6 (prev s 33B) ins A1998-51 s 5

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 71

4 Amendment history

		am A2001-44 amdt 1.1413 renum as s 34 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.27, amdt 2.28, amdt 2 amdt 2.40 renum as s 6 R10 LA (see A2004-13 amdt sub A2005-54 amdt 1.112	
	Exemption from	m s 5 and s 6 orig s 7 renum as s 22 and then s 21 (prev s 5C) ins A1994-52 s 6 renum as s 7 A1994-52 s 48 om A2004-13 amdt 2.24 pres s 7 (prev s 33C) ins A1998-51 s 5 renum as s 35 R4 LA (see A2000-69 s 29) renum as s 7 R10 LA (see A2004-13 amdt om A2005-54 amdt 1.112	2.43)
	Directions to r	ectify unsafe installations orig s 8 renum as s 23 and then s 22 (prev s 5D) ins A1994-52 s 6 renum as s 8 A1994-52 s 48 om A2004-13 amdt 2.24 pres s 8 (prev s 33D) ins A2000-69 s 9 renum as s 36 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.29 renum as s 8 R10 LA (see A2004-13 amdt am A2005-54 amdt 1.113; A2014-2 s 23, s R23 LA	
	Prescribed art	icles of electrical equipment orig pt 3 hdg renum as pt 4 hdg prev pt 3 hdg (prev pt 2 hdg) renum A1994 om A2004-13 amdt 2.24 pres pt 3 hdg (prev pt 7 hdg) sub Ord1985- A2000-69 s 11 renum as pt 3 hdg R10 LA (see A2004-13 a	20 s 4;
	Preliminary div 3.1 hdg	(prev pt 7 div 1 hdg) ins Ord1985-20 s 4 renum as div 7.1 hdg R4 LA (see A2000-69 renum as div 3.1 hdg R10 LA (see A2004-7	
	Definitions for s 9 hdg	pt 3 (prev s 32 hdg) renum as s 60 hdg A1994- sub A2000-69 s 12 renum as s 63 hdg R4 LA (see A2000-69 s	
	s 9	renum as s 9 hdg R10 LA (see A2004-13 a orig s 9 renum as s 24 and then s 23 (prev s 5E) ins A1994-52 s 6 renum as s 9 A1994-52 s 48	
page 72		Electricity Safety Act 1971 Effective: 06/03/14-17/04/14	R23 06/03/14

om A2004-13 amdt 2.24 pres s 9 (prev s 32) sub Ord1985-20 s 4 am Ord1989-38 sch 1; A1994-52 s 31 renum as s 60 A1994-52 s 48 am A1995-46 sch; A2000-69 s 12; A2001-44 amdt 1.1420, amdt 1.1421 renum as s 63 R4 LA (see A2000-69 s 29) renum as s 9 R10 LA (see A2004-13 amdt 2.43) am A2006-15 amdt 1.24

Declaration of corresponding law

s 10

orig s 10 renum as s 25 and then s 24 (prev s 5F) ins A1994-52 s 6 renum as s 10 A1994-52 s 48 om A2004-13 amdt 2.24 pres s 10 (prev s 32B) ins Ord1985-20 s 4 renum as s 62 A1994-52 s 48 am A2001-44 amdts 1.1422-1.1424 renum as s 64 R4 LA (see A2000-69 s 29) renum as s 10 R10 LA (see A2004-13 amdt 2.43) am A2012-21 amdt 3.58

Persons who may carry out incidental electrical work s 10A

renum as s 26 and then s 25

Regulation of dealings

div 3.2 hdg (prev pt 7 div 2 hdg) ins Ord1985-20 s 4 sub A2000-69 s 14 renum as div 7.2 hdg R4 LA (see A2000-69 s 29) renum as div 3.2 hdg R10 LA (see A2004-13 amdt 2.43)

Meaning of prescribed article of electrical equipment s 11

orig s 11 renum as s 27 and then s 26 (prev s 5G) ins A1994-52 s 6 renum as s 11 A1994-52 s 48 om A2004-13 amdt 2.24 pres s 11 (prev s 32D) ins Ord1985-20 s 4 renum as s 64 A1994-52 s 48 am A2000-69 sch 1; A2001-44 amdts 1.425-1.428 renum as s 65 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.41, amdt 2.42 renum as s 11 R10 LA (see A2004-13 amdt 2.43) sub A2006-15 amdt 1.25

Declaration of prescribed articles of electrical equipment ins A2006-15 amdt 1.25 s 11A

Declaration of articles not prescribed articles of electrical equipment ins A2006-15 amdt 1.25 s 11B

R23 06/03/14

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 73

Amendment history

4

s 12 hdg	(prev s 32E hdg) renum as s 65 hdg A1994-52 s 48
U	sub A2000-69 s 16
	renum as s 66 hdg R4 LA (see A2000-69 s 29)
40	renum as s 12 hdg R10 LA (see A2004-13 amdt 2.4
s 12	orig s 12 renum as s 28 and then s 27
	(prev s 5H) ins A1994-52 s 6 renum as s 12 A1994-52 s 48
	am A2002-11 amdt 2.37
	om A2004-13 amdt 2.24
	pres s 12 (prev s 32E) ins Ord1985-20 s 4
	am Ord1987-5 s 4, sch
	renum as s 65 A1994-52 s 48
	am A1994-81 sch; A2000-69 s 16
	renum as s 66 R4 LA (see A2000-69 s 29) renum as s 12 R10 LA (see A2004-13 amdt 2.43)
	sub A2005-54 amdt 1.114
Sale or install	ation of noncomplying prescribed articles
s 13 hdg	(prev s 32F hdg) renum as s 66 hdg A1994-52 s 48
ononag	sub A2000-69 s 17
	renum as s 67 hdg R4 LA (see A2000-69 s 29)
	renum as s 13 hdg R10 LA (see A2004-13 amdt 2.4
s 13	orig s 13 renum as s 29 and then s 28
	(prev s 5J) ins A1994-52 s 6
	renum as s 13 A1994-52 s 48 om A2004-13 amdt 2.24
	pres s 13 (prev s 32F) ins Ord1985-20 s 4
	am Ord1987-5 s 5
	renum as s 66 A1994-52 s 48
	am A1994-81 sch; A2000-69 s 17
	renum as s 67 R4 LA (see A2000-69 s 29)
	renum as s 13 R10 LA (see A2004-13 amdt 2.43) sub A2005-54 amdt 1.114
Carrying out o	of electrical wiring work by holder of electrician's per
grade A	of electrical withing work by holder of electricial s per
s 13A	renum as s 30 and then s 29
Carrying out of electrical licer	of incidental electrical work by holder of restricted nce
s 13B	renum as s 31 and then s 30
	of incidental electrical work by holder of restricted
electrical perm	
s 13C	renum as s 32 and then s 31

page 74

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

4

Registration as approved first seller orig s 14 renum as s 33 and then s 32 s 14 (prev s 5K) ins A1994-52 s 6 renum as s 14 A1994-52 s 48 om A1997-41 sch 1 prev s 14 (prev s 5L) ins A1994-52 s 6 renum as s 15 A1994-52 s 48 sub A2000-69 s 6 renum as s 14 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.24 pres s 14 (prev s 32G) ins Ord1985-20 s 4 am Ord1987-5 s 6, sch; Ord1988-31 sch; A1994-52 sch renum as s 67 A1994-52 s 48 am A1994-81 sch; A2000-69 sch 1; A2001-44 amdt 1.1429, amdt 1.1430 renum as s 68 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.39, amdt 2.40 renum as s 14 R10 LA (see A2004-13 amdt 2.43) am A2005-54 amdt 1.115; A2009-49 amdt 3.54; A2012-21 amdt 3.68 Application for registration of declaration of compliance orig s 15 renum as s 34 and then s 37 s 15 (prev s 5L) renum as s 15 and then s 14 (prev s 5M) ins A1994-52 s 6 renum as s 16 A1994-52 s 48 renum as s 15 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.24 pres s 15 (prev s 32H) ins Ord1985-20 s 4 renum as s 68 A1994-52 s 48 am A2000-69 sch 1; A2001-44 amdts 1.1431-1.1436 renum as s 69 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.39, amdt 2.40 renum as s 15 R10 LA (see A2004-13 amdt 2.43) am A2012-21 amdt 3.68 **Registration of declaration of compliance** s 16 orig s 16 renum as s 35 and then s 38 (prev s 5M) renum as s 16 and then s 15 (prev s 5N) ins A1994-52 s 6 renum as s 17 A1994-52 s 48 renum as s 16 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.24 pres s 16 (prev s 32J) ins Ord1985-20 s 4 renum as s 69 A1994-52 s 48 am A2000-69 sch 1; A2001-44 amdts 1.1437-1.1439 renum as s 70 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.39, amdt 2.40 R23 Electricity Safety Act 1971

06/03/14

Effective: 06/03/14-17/04/14

page 75

4 Amendment history

renum as s 16 R10 LA (see A2004-13 amdt 2.43) am A2012-21 amdt 3.60, amdt 3.61

Grant of electrical contractor's licence-partnership renum as s 36 and then s 39 s 16A Whether persons fit and proper s 16B renum as s 37 and then s 40 Public liability insurance s 16C renum as s 38 and then s 41 Suspension or cancellation of registration of declaration of compliance orig s 17 renum as s 39 and then s 42 s 17 (prev s 5N) renum as s 17 and then s 16 (prev s 5P) ins A1994-52 s 6 renum as s 18 A1994-52 s 48 renum as s 17 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.24 pres s 17 (prev s 32K) ins Ord1985-20 s 4 am Ord1988-31 sch renum as s 70 A1994-52 s 48 am A2000-69 sch 1; A2001-44 amdt 1.1440 renum as s 71 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.39, amdt 2.40 renum as s 17 R10 LA (see A2004-13 amdt 2.43) am A2012-21 amdt 3.68 Transfer of registration of declaration of compliance orig s 18 renum as 40 and then s 43 s 18 (prev s 5P) renum as s 18 and then s 17 (prev s 5Q) ins A1994-52 s 6 renum as s 19 A1994-52 s 48 renum as s 18 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.24 pres s 18 (prev s 32L) ins Ord1985-20 s 4 renum as s 71 A1994-52 s 48

am A2000-69 sch 1; A2001-44 amdt 1.1441, amdt 1.1442

renum as s 72 R4 LA (see A2000-69 s 29)

renum as s 18 R10 LA (see A2004-13 amdt 2.43)

page 76

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

am A2004-13 amdt 2.39

am A2012-21 amdt 3.68

4

Safety registration mark

s 19

s 20

orig s 19 renum as s 41 and then s 44 (prev s 5Q) renum as s 19 and then s 18 (prev s 5R) ins A1994-52 s 6 renum as s 20 A1994-52 s 48 am A2001-44 amdt 1.1411, amdt 1.1412 renum as s 19 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.24 pres s 19 (prev s 32M) ins Ord1985-20 s 4 am Ord1987-5 s 7, sch renum as s 72 A1994-52 s 48 am A1994-81 sch renum as s 73 R4 LA (see A2000-69 s 29) renum as s 19 R10 LA (see A2004-13 amdt 2.43) am A2005-54 amdt 1.116 am A2012-21 amdt 3.68

Approved testing laboratories

orig s 20 renum as s 42 and then s 45
(prev s 5R) renum as s 20 and then s 19
(prev s 6) renum as s 21 A1994-52 s 48
sub A2000-69 s 7
renum as s 20 R4 LA (see A2000-69 s 29)
om A2004-13 amdt 2.24
pres s 20 (prev s 32N) ins Ord1985-20 s 4
renum as s 73 A1994-52 s 48
am A2000-69 sch 1
renum as s 74 R4 LA (see A2000-69 s 29)
am A2004-13 amdt 2.41, amdt 2.42
renum as s 20 R10 LA (see A2004-13 amdt 2.43)
am A2012-21 amdt 3.68

Restricted electrical permit

s 20A renum as s 43 and then s 46

Licensing etc under mutual recognition principles s 20B renum as s 44 and then s 47

Application for licence

s 20C renum as s 45 and then s 48

Further information

s 20D renum as s 46 and then s 49

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 77

4 Amendment history

Registers s 21

orig s 21 renum as s 47 and then s 50 (prev s 6) renum as s 21 and then s 20 (prev s 7) renum as s 22 A1994-52 s 48 renum as s 21 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.24 pres s 21 (prev s 32P) ins Ord1985-20 s 4 renum as s 74 A1994-52 s 48 am A2000-69 sch 1; A2001-44 amdts 1.1443-1.1445 renum as s 75 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.39, amdt 2.40 renum as s 21 R10 LA (see A2004-13 amdt 2.43) am A2006-15 amdt 1.26; A2012-21 amdt 3.62, amdt 3.68

Examination and testing of articles s 22 orig s 22 renum a

	orig s 22 renum as s 48 and then s 51 (prev s 7) renum as s 22 and then s 21 (prev s 8) am A1994-52 s 7 renum as s 23 A1994-52 s 48 renum as s 22 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.24 pres s 22 (prev s 32Q) ins Ord1985-20 s 4 am Ord1987-5 s 8, sch renum as s 75 A1994-52 s 48 am A1994-81 sch; A2000-69 sch 1 renum as s 76 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.39, amdt 2.40 renum as s 22 R10 LA (see A2004-13 amdt 2.43) am A2005-54 amdt 1.117

Skills etc of applicants

s 22A renum as s 49 and then s 52

Licence conditions

s 22B renum as s 50 and then s 53

Imposition of conditions imposed under foreign law s 22C renum as s 51 and then s 54

Miscellaneous

div 3.3 hdg

(prev pt 7 div 4 hdg) ins Ord1985-20 s 4 renum as pt 7 div 3 hdg A2000-69 s 20 renum as div 7.3 hdg R4 LA (see A2000-79 s 29) renum as div 3.3 hdg R10 LA (see A2004-13 amdt 2.43)

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14

4

False representation

s 23

orig s 23 om A1994-52 s 20 (prev s 8) renum as s 23 and then s 22 (prev s 9) am A1994-52 s 8, sch renum as s 24 A1994-52 s 48 am A1994-81 sch renum as s 23 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.25 pres s 23 (prev s 32ZF) ins Ord1985-20 s 4 am Ord1987-5 sch renum as s 87 A1994-52 s 48 am A1994-81 sch renum as s 76 A2000-69 s 20 renum as s 77 R4 LA (see A2000-69 s 29) renum as s 23 R10 LA (see A2004-13 amdt 2.43) sub A2005-54 amdt 1.118

Evidence of registration of declaration of compliance s 24 orig s 24 renum as s 52 and then s 55

•	
	orig s 24 renum as s 52 and then s 55
	(prev s 9) renum as s 24 and then s 23
	(prev s 10) am A1994-52 s 9, sch
	renum as s 25 A1994-52 s 48
	am A1994-81 sch; A1999-53 s 5
	renum as s 24 R4 LA (see A2000-69 s 29)
	am A2003-37 amdt 2.7
	om A2004-13 amdt 2.25
	pres s 24 (prev s 32ZG) ins Ord1985-20 s 4
	renum as s 88 A1994-52 s 48
	am A2000-69 s 21
	renum as s 77 A2000-69 s 21
	renum as s 78 R4 LA (see A2000-69 s 29)
	am A2004-13 amdt 2.39
	renum as s 24 R10 LA (see A2004-13 amdt 2.43)

Non-prescribed articles of electrical equipment pt 4 hdg orig pt 4 hdg renum as pt 5 hdg

orig pt 4 hdg renum as pt 5 hdg prev pt 4 hdg (prev pt 3 hdg) renum as pt 2 hdg pres pt 4 hdg (prev pt 7A hdg) ins A2000-69 s 23 renum as pt 8 hdg R4 LA (see A2000-69 s 29) renum as pt 4 hdg R10 LA (see A2004-13 amdt 2.43)

Articles to which pt 4 applies

s 25	orig s 25 renum as s 53 and then s 56
	(prev s 10) renum as s 25 and then s 24
	(prev s 10A) ins A1994-52 s 10
	renum as s 26 A1994-52 s 48
	am A1998-54 sch
	renum as s 25 R4 LA (see A2000-69 s 29)
	om A2004-13 amdt 2.25

R23	Electricity Safety Act 1971	page 79
06/03/14	Effective: 06/03/14-17/04/14	

4 Amendment history

pres s 25 (prev s 78) ins A2000-69 s 23 renum as s 79 R4 LA (see A2000-69 s 29) renum as s 25 R10 LA (see A2004-13 amdt 2.43) am A2012-32 s 38, s 39

Minimum safety standards

s 26 orig s 26 renum as s 54 and then s 57 (prev s 10A) renum as s 26 and then s 25 (prev s 11) am A1994-52 s 11, sch renum as s 27 A1994-52 s 48 am A1994-81 sch renum as s 26 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.25 pres s 26 (prev s 79) ins A2000-69 s 23 renum as s 80 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.31 renum as s 26 R10 LA (see A2004-13 amdt 2.43) am A2005-54 amdt 1.119

Offences—energy efficiency requirements for non-prescribed articles of electrical equipment

s 27

orig s 27 renum as s 55 and then s 58 (prev s 11) renum as s 27 and then s 26 (prev s 12) am Ord1972-27 s 2; A1994-52 sch renum as s 28 A1994-52 s 48 am A1994-81 sch renum as s 27 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.25 pres s 27 (prev s 79A) ins A2000-69 s 23 renum as s 81 R4 LA (see A2000-69 s 29) renum as s 27 R10 LA (see A2000-69 s 29) am A2005-54 amdt 1.120, amdt 1.121 sub A2014-2 s 25

Cancellation of licence on basis of action under foreign law s 27A renum as s 56 and then s 59

Defective articles of electrical equipment

pt 5 hdg orig pt 5 hdg renum as pt 6 hdg prev pt 5 hdg (prev pt 4 hdg) am A1994-52 s 14 renum as pt 5 hdg A1994-52 s 48 om A2004-13 amdt 2.30 pres pt 5 hdg (prev pt 7B hdg) ins A2000-69 s 23 renum as pt 9 hdg R4 LA (see A2000-69 s 29) renum as pt 5 hdg R10 LA (see A2004-13 amdt 2.43)

page 80

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

4

Prohibited articles

s 28

orig s 28 renum as s 57 and then s 60 (prev s 12) renum as s 28 and then s 27 (prev s 13) am Ord1972-27 s 3; A1994-52 s 12, sch renum as s 29 A1994-52 s 48 am A1994-81 sch renum as s 28 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.25 pres s 28 (prev s 80) ins A2000-69 s 23 am A2001-44 amdt 1.1446, amdt 1.1447 renum as s 82 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.41 renum as s 28 R10 LA (see A2004-13 amdt 2.43) am A2009-20 amdt 3.65; A2012-21 amdt 3.63

Sale or installation of prohibited articles

s 29	orig s 29 renum as s 58 and then s 61
	(prev s 13) renum as s 29 and then s 28
	(prev s 13A) ins A1994-52 s 13
	renum as s 30 A1994-52 s 48
	am A1998-54 sch
	renum as s 29 R4 LA (see A2000-69 s 29)
	om A2004-13 amdt 2.25
	pres s 29 (prev s 81) ins A2000-69 s 23
	renum as s 83 R4 LA (see A2000-69 s 29)
	renum as s 29 R10 LA (see A2004-13 amdt 2.43)
	sub A2005-54 amdt 1.122

Directions about unsafe articles s 30 orig s 30 renun

orig s 30 renum as s 59 and then s 62 (prev s 13A) renum as s 30 and then s 29 (prev s 13B) ins A1994-52 s 13 renum as s 31 A1994-52 s 48 am A1998-54 sch renum as s 30 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.25 pres s 30 (prev s 82) ins A2000-69 s 23 renum as s 84 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.41, amdt 2.42 renum as s 30 R10 LA (see A2004-13 amdt 2.43) am A2005-54 amdt 1.123; A2012-21 amdt 3.64

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 81

4 Amendment history

Publication of safety warnings				
s 31	orig s 31 am Ord1985-67 sch pt 1			
	om A1994-52 s 30			
	(prev s 13B) renum as s 31 and then s 30			
	(prev s 13C) ins A1994-52 s 13			
	renum as s 32 A1994-52 s 48			
	am A1998-54 sch			
	renum as s 31 R4 LA (see A2000-69 s 29)			
	om A2004-13 amdt 2.25			
	pres s 31 (prev s 83) ins A2000-69 s 23			
	renum as s 85 R4 LA (see A2000-69 s 29)			
	am A2004-13 amdt 2.41			
	renum as s 31 R10 LA (see A2004-13 amdt 2.43) am A2007-39 amdt 3.35			
	am A2007-39 amut 3.35			
Serious electrica	al accidents			
pt 6 hdg	orig pt 6 hdg om A1994-52 s 30			
	prev pt 6 hdg (prev pt 5 hdg) am A1994-52 s 24			
	renum A1994-52 s 48			
	om A2004-13 amdt 2.30			
	pres pt 6 hdg (prev pt 7C hdg) ins A2000-69 s 23			
	renum as pt 10 hdg R4 LA (see A2000-69 s 29)			
	renum as pt 6 hdg R10 LA (see A2004-13 amdt 2.43)			
Definitions for p	t 6			
s 32	orig s 32 renum as s 60 and then s 63			
	(prev s 13C) renum as s 32 and then s 31			
	(prev s 14) renum as s 33 and then s 32 and then s 4			
	pres s 32 (prev s 84) ins A2000-69 s 23			
	renum as s 86 R4 LA (see A2000-69 s 29)			
	renum as s 32 R10 LA (see A2004-13 amdt 2.43)			
Application of pa	art			
s 32A	renum as s 61			
	prresponding law			
s 32B	renum as s 62 and then s 64 and then s 10			
Prohibition of sa	le, installation or regulation of articles of electrical			
equipment				
s 32C	renum as s 63			
Prescribed articl	es of electrical equipment			
s 32D	renum as s 64 and then s 65 and then s 11			
3 020				
	etc of prescribed articles			
s 32E	renum as s 65 and then s 66 and then s 12			
Sale etc of article	es not complying with standards			
s 32F	renum as s 66 and then s 67 and then s 13			
-				

page 82

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

Registration as a p s 32G	pproved first seller renum as s 67 and then s 68 and then s 14
Application for reals 32H	gistration of declaration of compliance renum as s 68 and then s 69 and then s 15
Registration of de s 32J	claration of compliance renum as s 69 and then s 70 and then s 16
Suspension or ca s 32K	ncellation of registration of declaration of compliance renum as s 70 and then s 71 and then s 17
Fransfer of regist	ration of declaration of compliance renum as s 71 and then s 72 and then s 18
Safety registratio s 32M	n mark renum as s 72 and then s 73 and then s 19
Approved testing § 32N	laboratories renum as s 73 and then s 74 and then s 20
Registers s 32P	renum as s 74 and then s 75 and then s 21
Examination and t s 32Q	testing of articles renum as s 75 and then s 76 and then s 22
Unsafe articles s 32R	renum as s 76
Public statements	s by authority renum as s 77
Inspectors s 32T	renum as s 78
Return of identity s 32U	card renum as s 79
Powers of inspect s 32V	t ors renum as s 80
Interpretation s 32W	renum as s 81
Entry and search s 32X	etc renum as s 82
Publication of saf	ety warnings renum as s 83
Search warrants s 32Y	renum as s 84

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 83

4 Amendment history

Search warrants may be granted by telephone

s 32Z ins Ord1985-20 s 4 om Ord1987-5 s 14 Entry etc in emergencies ins Ord1985-20 s 4 32ZA

om Ord1987-5 s 14 **Obstruction of inspectors**

s 32ZB renum as s 85

Review of inspector's direction s 32ZC renum as s 86

Review by administrative appeals tribunal

ins Ord1985-20 s 4 s 32ZD am Ord1987-5 s 16 om A1994-52 s 32

Notifications of decisions

s 32ZE ins Ord1985-20 s 4

am Ord1989-38 sch 1 om A1994-52 s 32

False representation

s 32ZF renum as s 87 and then s 76 and then s 77 and then s 23

Evidence of registration of declaration of compliance

renum as s 88 and then s 77 and then s 78 and then s 24 s 32ZG

Service of documents s 32ZH

renum as s 89

Determination of fees s 32ZJ

ins Ord1985-20 s 4 om A1994-52 s 32

Reporting by occupiers and electrical contractors

s 33 orig s 33 renum as s 90

(prev s 14) renum as s 33 and then s 32 and then s 4 (prev s 33A) renum as s 33 and then s 5 pres s 33 (prev s 85) ins A2000-69 s 23 renum as s 87 R4 LA (see A2000-69 s 29) renum as s 33 R10 LA (see A2004-13 amdt 2.43) sub A2005-54 amdt 1.124

Compliance with Australian Standard 3000

renum as s 33 and then s 5 s 33A

Testing and reporting of electrical work

s 33B renum as s 34 and then s 6

page 84

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14

R23 06/03/14

4

Exemption from s 33 and s 34

s 33C renum as s 35 and then s 7

Directions to rectify unsafe installations s 33D renum as s 36 and then s 8

Reporting by electricity distributor

s 34 orig s 34 renum as s 91 (prev s 15) renum as s 34 and then s 37 (prev s 33B) renum as s 34 and then s 6 pres s 34 (prev s 86) ins A2000-69 s 23 renum as s 88 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.39 renum as s 34 R10 LA (see A2004-13 amdt 2.43) sub A2005-54 amdt 1.124 am A2013-31 s 75

Interference with site of serious electrical accident s 35 orig s 35 renum as s 92

orig s 35 renum as s 92 (prev s 16) renum as s 35 and then s 38 (prev s 33C) renum as s 35 and then s 7 pres s 35 (prev s 87) ins A2000-69 s 23 renum as s 89 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.39 renum as s 35 R10 LA (see A2004-13 amdt 2.43) sub A2005-54 amdt 1.124 am A2012-21 amdt 3.65

Publication of report of serious electrical accident s 36 orig s 36 renum as s 93

orig s 36 renum as s 93 (prev s 16A) renum as s 36 and then s 39 (prev s 33D) renum as s 36 and then s 8 pres s 36 (prev s 88) ins A2000-69 s 23 renum as s 90 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.41 renum as s 36 R10 LA (see A2004-13 amdt 2.43) am A2007-39 amdt 3.36

Review of decisions

s 36AA renum as s 94 and then s 119 and then s 61

Notifications of decisions

s 36AB renum as s 95 and then s 120 and then s 62

Conduct of directors, servants and agents

```
s 36A renum as s 96 and then s 121
```

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 85

4	Amendment history	
---	-------------------	--

Enforcement

pt 7 hdg	orig pt 7 hdg renum as pt 3 hdg (prev pt 7D hdg) ins A2000-69 s 23 renum as pt 11 hdg R4 LA (see A2000-69 s 29) renum as pt 7 hdg R10 LA (see A2004-13 amdt 2.43)
General div 7.1 hdg	prev div 7.1 hdg renum as div 3.1 hdg (prev pt 7D div 1 hdg) ins A2000-69 s 23 renum as div 11.1 hdg R4 LA (see A2000-69 s 29) renum as div 7.1 hdg R10 LA (see A2004-13 amdt 2.43)
Definition of busin	ness premises
s 37	orig s 37 renum as s 97 and then s 122 (prev s 16B) renum as s 37 and then s 40 (prev s 15) am Ord1972-27 s 4 sub A1994-52 s 15 renum as s 34 A1994-52 s 48 am A2000-69 sch 1 renum as s 37 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 37 (prev s 89) ins A2000-69 s 23 renum as s 91 R4 LA (see A2000-69 s 29) renum as s 37 R10 LA (see A2004-13 amdt 2.43)
Things connected	with offences
s 38	orig s 38 renum as s 98 and then s 123 (prev s 16C) renum as s 38 and then s 41 (prev s 16) sub A1994-52 s 15 renum as s 35 A1994-52 s 48 renum as s 38 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 38 (prev s 89A) ins A2000-69 s 23 renum as s 92 R4 LA (see A2000-69 s 29) renum as s 38 R10 LA (see A2004-13 amdt 2.43)

Planning and land authority may require information and documents s 39 hdg (prev s 93 hdg) am A2004-13 amdt 2.41

s 39 hdg	(prev s 93 hdg) am A2004-13 amdt 2.41
	renum as s 39 hdg R10 LA (see A2004-13 amdt 2.43)
s 39	orig s 39 renum as s 99 and then s 124
	(prev s 17) renum as s 39 and then s 42
	(prev s 16A) ins A1994-52 s 15
	renum as s 36 A1994-52 s 48
	renum as s 39 R4 LA (see A2000-69 s 29)
	om A2004-13 amdt 2.30
	pres s 39 (prev s 89B) ins A2000-69 s 23
	renum as s 93 R4 LA (see A2000-69 s 29)
	am A2004-13 amdt 2.41, amdt 2.42
	renum as s 39 R10 LA (see A2004-13 amdt 2.43)

page 86	Electricity Safety Act 1971	R23
	Effective: 06/03/14-17/04/14	06/03/14

	Amendment history	4
	requirement by planning and land authority	
s 40 hdg	(prev s 94 hdg) am A2004-13 amdt 2.41 renum as s 40 hdg R10 LA (see A2004-13 amdt 2.43)	
s 40	orig s 40 renum as s 100 and then s 125	
3 40	(prev s 18) renum as s 40 and then s 43	
	(prev s 16B) ins A1994-52 s 15	
	renum as s 37 A1994-52 s 48	
	renum as s 40 R4 LA (see A2000-69 s 29)	
	om A2004-13 amdt 2.30	
	pres s 40 (prev s 89C) ins A2000-69 s 23	
	renum as s 94 R4 LA (see A2000-69 s 29)	
	renum as s 40 R10 LA (see A2004-13 amdt 2.43)	
	sub A2005-54 amdt 1.125	
Appointment of i		
s 41	orig s 41 renum as s 101 and then s 126	
	(prev s 19) renum as s 41 and then s 44	
	(prev s 16C) ins A1994-52 s 15	
	renum as s 38 A1994-52 s 48 renum as s 41 R4 LA (see A2000-69 s 29)	
	om A2004-13 amdt 2.30	
	pres s 41 (prev s 89D) ins A2000-69 s 23	
	am A2001-44 amdt 1.448	
	renum as s 95 R4 LA (see A2000-69 s 29)	
	am A2004-13 amdt 2.39, amdt 2.40	
	renum as s 41 R10 LA (see A2004-13 amdt 2.43)	
	am A2007-39 amdt 3.37	
Identity cards		
s 42	orig s 42 renum as s 102 and then s 127	
	(prev s 20) renum as s 42 and then s 45	
	(prev s 17) am A1994-52 s 16, sch	
	renum as s 39 A1994-52 s 48	
	renum as s 42 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30	
	pres s 42 (prev s 89E) ins A2000-69 s 23	
	renum as s 96 R4 LA (see A2000-69 s 29)	
	am A2004-13 amdt 2.39	
	renum as s 42 R10 LA (see A2004-13 amdt 2.43)	
	sub A2005-54 amdt 1.126	
	(5)-(7) exp 24 November 2005 (s 42 (7))	
Inspectors' powe	ers	
div 7.2 hdg	prev div 7.2 hdg renum as div 3.2 hdg	
	(prev pt 7D div 2 hdg) ins A2000-69 s 23	
	renum as div 11.2 hdg R4 LA (see A2000-69 s 29)	
	renum as div 7.2 hdg R10 LA (see A2004-13 amdt 2.4	3)

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 87

4 Amendment history

s 43	orig s 43 renum as s 103 (prev s 20A) renum as s 43 and then s 46 (prev s 18) am Ord1978-46 sch 2; A1994-52 sch renum as s 40 A1994-52 s 48 sub A2000-69 s 10 renum as s 43 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 43 (prev s 89F) ins A2000-69 s 23 renum as s 97 R4 LA (see A2000-69 s 29) renum as s 43 R10 LA (see A2004-13 amdt 2.43)
Approved forms s 43AA	renum as s 104 and then s 129 and then s 65
Payment of fees s 43A	renum as s 105
Production of ide s 44	ntity card orig s 44 renum as s 106 (prev s 20B) renum as s 44 and then s 47 (prev s 19) sub A1994-52 s 17 renum as s 41 A1994-52 s 48 renum as s 44 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 44 (prev s 89G) ins A2000-69 s 23 renum as s 98 R4 LA (see A2000-69 s 29) renum as s 44 R10 LA (see A2004-13 amdt 2.43)
Consent to entry s 45	(prev s 20C) renum as s 45 and then s 48 (prev s 20) sub A1994-52 s 17 renum as s 42 A1994-52 s 17 renum as s 45 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 45 (prev s 89H) ins A2000-69 s 23 renum as s 99 R4 LA (see A2000-69 s 29) renum as s 45 R10 LA (see A2004-13 amdt 2.43)
Warrants s 46	(prev s 20D) renum as s 46 and then s 49 (prev s 20A) ins A1994-52 s 17 renum as s 43 A1994-52 s 48 am A2000-69 sch 1 renum as s 46 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 46 (prev s 89J) ins A2000-69 s 23 renum as s 100 R4 LA (see A2000-69 s 29) renum as s 46 R10 LA (see A2004-13 amdt 2.43)

page 88

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

Warrants-application made other than in person (prev s 21) renum as s 47 and then s 50 s 47 (prev s 20B) ins A1994-52 s 17 renum as s 44 A1994-52 s 48 renum as s 47 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 47 (prev s 89K) ins A2000-69 s 23 renum as s 101 R4 LA (see A2000-69 s 29) renum as s 47 R10 LA (see A2004-13 amdt 2.43) Powers on entry to premises s 48 (prev s 22) renum as s 48 and then s 51 (prev s 20C) ins A1994-52 s 17 renum as s 45 A1994-52 s 48 sub A2001-44 amdt 1.1414 renum as s 48 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 48 (prev s 89L) ins A2000-69 s 23 renum as s 102 R4 LA (see A2000-69 s 29) renum as s 48 R10 LA (see A2004-13 amdt 2.43) am A2005-54 amdt 1.127 Powers in relation to serious electrical accidents s 49 (prev s 22A) renum as s 49 and then s 52 (prev s 20D) ins A1994-52 s 17 renum as s 46 A1994-52 s 48 renum as s 49 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 49 (prev s 89M) ins A2000-69 s 23 renum as s 103 R4 LA (see A2000-69 s 29) renum as s 49 R10 LA (see A2004-13 amdt 2.43) Powers in relation to unsafe articles of electrical equipment s 50 (prev s 22B) renum as s 50 and then s 53 (prev s 21) am A1994-52 sch renum as s 47 A1994-52 s 48 am A1994-81 sch renum as s 50 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 50 (prev s 89N) ins A2000-69 s 23 sub A2001-44 amdt 1.1451 renum as s 104 R4 LA (see A2000-69 s 29) renum as s 50 R10 LA (see A2004-13 amdt 2.43) am A2005-54 amdt 1.128

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 89

Amendment history

4

s 51 hdg	etc dangerous electrical equipment and installatic (prev s 105 hdg) sub A2004-13 amdt 2.32
s 51	renum as s 51 hdg R10 LA (see A2004-13 amdt 2 (prev s 22C) renum as s 51 and then s 54 (prev s 22) am A1994-52 s 18, sch renum as s 48 A1994-52 s 48 renum as s 51 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 51 (prev s 89P) ins A2000-69 s 23 renum as s 105 R4 LA (see A2000-69 s 29) renum as s 51 R10 LA (see A2004-13 amdt 2.43) am A2005-54 amdt 1.129
Power to requi	re name and address
s 52	(prev s 24) renum as s 52 and then s 55 (prev s 22A) ins A1994-52 s 19 renum as s 49 A1994-52 s 48 renum as s 52 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 52 (prev s 89Q) ins A2000-69 s 23 renum as s 106 R4 LA (see A2000-69 s 29) renum as s 52 R10 LA (see A2004-13 amdt 2.43) sub A2005-54 amdt 1.130 am A2009-49 amdt 3.55
Power to seize	
s 53	(prev s 25) renum as s 53 and then s 56 (prev s 22B) ins A1994-52 s 19 renum as s 50 A1994-52 s 48 renum as s 53 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 53 (prev s 89R) ins A2000-69 s 23 renum as s 107 R4 LA (see A2000-69 s 29) am R10 LA (see A2004-13 amdt 2.39) renum as s 53 R10 LA (see A2004-13 amdt 2.43) am A2005-54 amdt 1.131
Receipt for thin	
s 54	(prev s 26) renum as s 54 and then s 57 (prev s 22C) ins A1994-52 s 19 renum as s 51 A1994-52 s 48 renum as s 54 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 54 (prev s 89S) ins A2000-69 s 23 renum as s 108 R4 LA (see A2000-69 s 29) renum as s 54 R10 LA (see A2004-13 amdt 2.43)

page 90

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

4

Access to things seized

Access to things	Seizeu
s 55	(prev s 27) renum as s 55 and then s 58 (prev s 24) am Ord1978-46 sch 2 sub A1994-52 s 21 renum as s 52 A1994-52 s 48 am A2001-44 amdts 1.1415-1.1418 renum as s 55 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 55 (prev s 89T) ins A2000-69 s 23 renum as s 109 R4 LA (see A2000-69 s 29) renum as s 55 R10 LA (see A2004-13 amdt 2.43)
Return of things s	seized
s 56	(prev s 27A) renum as s 56 and then s 59 (prev s 25) am A1994-52 s 22 renum as s 53 A1994-52 s 48 renum as s 56 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 56 (prev s 89U) ins A2000-69 s 23 renum as s 110 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.39 renum as s 56 R10 LA (see A2004-13 amdt 2.43)
Power to inspect	electrical wiring work
s 57	(prev s 28) renum as s 57 and then s 60 (prev s 26) am A1994-52 s 23 renum as s 54 A1994-52 s 48 am A2001-44 amdt 1.1419 renum as s 57 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 57 (prev s 89V) ins A2000-69 s 23 renum as s 111 R4 LA (see A2000-69 s 29) renum as s 57 R10 LA (see A2004-13 amdt 2.43) am A2014-2 s 26
Miscellaneous	

Miscellaneous

div 7.3 hdg orig pt 7 div 3 hdg ins Ord1985-20 s 4 om A2000-69 s 19 prev div 7.3 hdg (prev div 7.4 hdg) renum as div 3.3 hdg (prev pt 7D div 3 hdg) ins A2000-69 s 23 renum as div 11.3 hdg R4 LA (see A2000-69 s 29) renum as div 7.3 hdg R10 LA (see A2004-13 amdt 2.43)

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 91

4 Amendment history

Self-incrimination etc s 58 (prev s 29) renum as s 58 and then s 61 (prev s 27) am Ord1972-27 s 5; Ord1988-31 sch; A1994-52 s 25, sch renum as s 55 A1994-52 s 48 am A1997-96 sch 1; A2000-69 sch 1; A2000-66 sch 1 pt 4 renum as s 58 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 58 (prev s 89W) ins A2000-69 s 23 renum as s 112 R4 LA (see A2000-69 s 29) am A2002-11 amdt 2.37; A2002-51 amdt 1.19 renum as s 58 R10 LA (see A2004-13 amdt 2.43) Damage etc to be minimised s 59 (prev s 30) renum as s 59 and then s 62 (prev s 27A) ins A1994-52 s 26 renum as s 56 A1994-52 s 48 renum as s 59 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 59 (prev s 89ZB) ins A2000-69 s 23 renum as s 117 R4 LA (see A2000-69 s 29) renum as s 59 R10 LA (see A2004-13 amdt 2.43) Compensation s 60 (prev s 32) renum as s 60 and then s 63 (prev s 28) am A1991-3 sch; A1994-52 s 27, sch renum as s 57 A1994-52 s 48 renum as s 60 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 60 (prev s 89ZC) ins A2000-69 s 23 renum as s 118 R4 LA (see A2000-69 s 29) renum as s 60 R10 LA (see A2004-13 amdt 2.43) Non-prescribed articles of electrical equipment pt 7A hdg renum as pt 8 hdg and then pt 4 hdg Defective articles of electrical equipment pt 7B hdg renum as pt 9 hdg and then pt 5 hdg Serious electrical accidents pt 7C hdg renum as pt 10 hdg and then pt 6 hdg Enforcement pt 7D hdg renum as pt 11 hdg and then pt 7 hdg General pt 7D div 1 hdg renum as div 11.1 hdg and then div 7.1 hdg Inspectors' powers pt 7D div 2 hdg renum as div 11.2 hdg and then div 7.2 hdg

page 92

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

Miscellaneous

pt 7D div 3 hdg renum as div 11.3 hdg and then div 7.3 hdg

Appeals pt 8 hdg

s 61

S

orig pt 8 hdg om A2000-66 sch 1 pt 4 (prev pt 7A hdg) renum as pt 8 hdg and then pt 4 hdg (prev pt 8A hdg) ins A1994-52 s 34 renum as pt 9 hdg A1994-52 s 48 renum as pt 12 hdg R4 LA (see A2000-69 s 29) renum as pt 8 hdg R10 LA (see A2004-13 amdt 2.43) sub A2008-37 amdt 1.154

Meaning of reviewable decision-pt 8

(prev s 32A) ins Ord1985-20 s 4 renum as s 61 A1994-52 s 48 om A2000-69 s 13 (prev s 29) am A1994-52 s 28, sch renum as s 58 A1994-52 s 48 renum as s 61 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.30 pres s 61 (prev s 36AA) ins A1994-52 s 34 renum as s 94 A1994-52 s 48 am A2000-66 sch 1 pt 4; A2000-69 s 25 renum as s 119 R4 LA (see A2000-69 s 29) sub A2004-13 amdt 2.33 renum as s 61 R10 LA (see A2004-13 amdt 2.43) am A2006-15 amdt 1.27 sub A2008-37 amdt 1.154

Reviewable decision notices

s 62	(prev s 32B) renum as s 62 and then s 64 and then s 10
	(prev s 30) am A1994-52 s 29, sch
	renum as s 59 A1994-52 s 48
	renum as s 62 R4 LA (see A2000-69 s 29)
	om A2004-13 amdt 2.30
	pres s 62 (prev s 36AB) ins A1994-52 s 34
	renum as s 95 A1994-52 s 48
	am A1994-60 sch 1; A2000-66 sch 1 pt 4; A2000-69 s 26
	renum as s 120 R4 LA (see A2000-69 s 29)
	renum as s 62 R10 LA (see A2004-13 amdt 2.43)
	sub A2008-37 amdt 1.154

Applications for review

ins A2008-37 amdt 1.154

Appeals

s 62A

pt 8A hdg

renum as pt 9 hdg and then pt 12 hdg and then pt 8 hdg

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 93

4

Amendment history	
Miscellaneous pt 9 hdg	(prev pt 8A hdg) renum as pt 9 hdg and then pt 12 hdg and then pt 8 hdg (prev pt 7B hdg) renum as pt 9 hdg and then pt 5 hdg pres pt 9 hdg (prev pt 9 hdg) renum as pt 10 hdg A1994-52 s 48 renum as pt 13 hdg R4 LA (see A2000-69 s 29) renum as pt 9 hdg R10 LA (see A2004-13 amdt 2.43)
Evidence s 63	(prev s 32C) ins Ord1985-20 s 4 am Ord1987-5 s 3, sch renum as s 63 A1994-52 s 48 am A1994-81 sch om A2000-69 s 15 (prev s 32) renum as s 60 and then s 63 and then s 9 pres s 63 (prev s 41) am Ord1988-31 sch; A1994-52 s 39, sch renum as s 101 A1994-52 s 48 am A2000-69 sch 1 renum as s 126 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.35, amdt 2.39 renum as s 63 R10 LA (see A2004-13 amdt 2.43)
Determination of a s 64	am A2012-21 amdt 3.66 fees (prev s 32D) renum as s 64 and then s 65 and then s 11 (prev s 32B) renum as s 62 and then s 64 and then s 10 (prev s 103) ins A2001-44 amdt 1.1451 renum as s 128 R4 LA (see A2000-69 s 29) renum as s 64 R10 LA (see A2004-13 amdt 2.43) am A2007-39 amdt 3.38
Approved forms s 65	(prev s 32E) renum as s 65 and then s 66 and then s 12 (prev s 32D) renum as s 64 and then s 65 and then s 11 (prev s 43AA) ins A1994-52 s 41 renum as s 104 A1994-52 s 48 sub A2001-44 amdt 1.1451 renum as s 129 R4 LA (see A2000-69 s 29) am A2004-13 amdt 2.39 renum as s 65 R10 LA (see A2004-13 amdt 2.43) am A2007-39 amdt 3.38, amdt 3.39

page 94

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

4

Regulation-making power

s 66	(prev s 32F) renum as s 66 and then s (prev s 32E) renum as s 65 and then s (prev s 105) ins A2001-44 amdt 1.1451 renum as s 130 R4 LA (see A2000-69 s renum as s 66 R10 LA (see A2004-13 a am A2014-2 s 27	66 and then s 12 s 29)
New regulations s 67	(prev s 32G) renum as s 67 and then s (prev s 32F) renum as s 66 and then s (prev s 131) ins A2004-13 amdt 2.37 renum as s 67 R10 LA (see A2004-13 a exp 1 September 2004 (s 131 (5))	67 and then s 13
Registration as a s 68	approved first seller (prev s 32H) renum as s 68 and then s (prev s 32G) renum as s 67 and then s	
Application for ros	egistration of declaration of complianc (prev s 32J) renum as s 69 and then s (prev s 32H) renum as s 68 and then s	70 and then s 16
Registration of d s 70	eclaration of compliance (prev s 32K) renum as s 70 and then s (prev s 32J) renum as s 69 and then s	
Suspension or ca s 71	ancellation of registration of declaratio (prev s 32L) renum as s 71 and then s (prev s 32K) renum as s 70 and then s	72 and then s 18
Transfer of regis s 72	tration of declaration of compliance (prev s 32M) renum as s 72 and then s (prev s 32L) renum as s 71 and then s	73 and then s 19 72 and then s 18
Safety registratio s 73	on mark (prev s 32N) renum as s 73 and then s (prev s 32M) renum as s 72 and then s	74 and then s 20 73 and then s 19
Approved testing s 74	g laboratories (prev s 32P) renum as s 74 and then s (prev s 32N) renum as s 73 and then s	
Registers s 75	(prev s 32Q) renum as s 75 and then s (prev s 32P) renum as s 74 and then s	
Examination and s 76	I testing of articles (prev s 32R) ins Ord1985-20 s 4 am Ord1987-5 s 9, sch renum as s 76 A1994-52 s 48 am A1994-81 sch	
	Electricity Safety Act 1971	page 95

06/03/14

R23

Effective: 06/03/14-17/04/14

4 Amendment history

om A2000-69 s 18 (prev s 32ZF) renum as s 87 and then s 76 and then s 77 and then s 23 (prev s 32Q) renum as s 75 and then s 76 and then s 22 **False representation** s 77 (prev s 32S) ins Ord1985-20 s 4 renum as s 77 A1994-52 s 48 om A2000-69 s 18 (prev s 32ZG) renum as s 88 and then s 77 and then s 78 and then s 24 (prev s 32ZF) renum as s 87 and then s 76 and then s 77 and then s 23 Evidence of registration of declaration of compliance (prev s 32T) ins Ord1985-20 s 4 s 78 am Ord1988-31 sch renum as s 78 A1994-52 s 48 om A2000-69 s 19 ins A2000-69 s 23 renum as s 79 (prev s 32ZG) renum as s 88 and then s 77 and then s 78 and then s 24 Articles to which pt 8 applies s 79 (prev s 32U) ins Ord1985-20 s 4 am Ord1987-5 sch renum as s 79 A1994-52 s 48 am A1994-81 sch om A2000-69 s 19 (prev s 78) renum as s 79 and then s 25 **Energy efficiency requirements** s 79A renum as s 81 and then s 27 Minimum safety standards (prev s 32V) ins Ord1985-20 s 4 s 80 am Ord1987-5 s 10, sch renum as s 80 A1994-52 s 48 am A1994-81 sch om A2000-69 s 19 (prev s 79) renum as s 80 and then s 26 **Energy efficiency requirements** s 81 (prev s 32W) ins Ord1985-20 s 4 renum as s 81 A1994-52 s 48 om A2000-69 s 19 (prev s 79A) renum as s 81 and then s 27

page 96

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

Prohibited arti	cles
s 82	(prev s 32X) ins Ord1985-20 s 4 am Ord1987-5 s 11 renum as s 82 A1994-52 s 48 om A2000-69 s 19 (prev s 80) renum as s 82 and then s 28
Sale or installa	ation of prohibited articles
s 83	(prev s 32XA) ins Ord1987-5 s 12 renum as s 83 A1994-52 s 48 om A2000-69 s 19 (prev s 81) renum as s 83 and then s 29
Directions abo	out unsafe articles
s 84	(prev s 32Y) ins Ord1985-20 s 4 am Ord1987-5 s 13 renum as s 84 A1994-52 s 48 om A2000-69 s 19 (prev s 82) renum as s 84 and then s 30
Publication of	safety warnings
s 85	(prev s 32ZB) ins Ord1985-20 s 4 sub Ord1987-5 s 15 renum as s 85 A1994-52 s 48 am A1994-81 sch om A2000-69 s 19 (prev s 83) renum as s 85 and then s 31
Serious electri	ical accidents
pt 10 hdg	(prev pt 9 hdg) renum as pt 10 hdg and then pt 13 hd and then pt 9 hdg prev pt 10 hdg (prev pt 7C hdg) renum as pt 6 hdg
Definitions for	nt 10
s 86	(prev s 32ZC) ins Ord1985-20 s 4 renum as s 86 A1994-52 s 48 am A2000-66 sch 1 pt 4 om A2000-69 s 19 (prev s 84) renum as s 86 and then s 32
Reporting by c	occupiers and electrical contractors
s 87	(prev s 32ZF) renum as s 87 and then s 76 and then s and then s 23 (prev s 85) renum as s 87 and then s 33
	electricity distributor
Reporting by e	(prev s 32ZG) renum as s 88 and then s 77 and then
Reporting by e s 88	and then s 24

R23 06/03/14

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 97

4 Amendment history

Interference with s 89	site of serious electrical accident (prev s 32ZH) ins Ord1985-20 s 4 renum as s 89 A1994-52 s 48 om A2000-69 s 22 (prev s 87) renum as s 89 and then s 35
Things connected	l with offences
s 89A	renum as s 92 and then s 38
Chief executive m	ay require information and documents
s 89B	renum as s 93 and then s 39
Contravention of s 89C	requirement by chief executive renum as s 94 and then s 40
Appointment of in	ispectors
s 89D	renum as s 95 and then s 41
Identity cards s 89E	renum as s 96 and then s 42
General power to	enter premises
s 89F	renum as s 97 and then s 43
Production of ide	ntity card
s 89G	renum as s 98 and then s 44
Consent to entry s 89H	renum as s 99 and then s 45
Warrants s 89J	renum as s 100 and then s 46
Warrants—applica	ation made other than in person
s 89K	renum as s 101 and then s 47
Powers on entry t	o premises
s 89L	renum as s 102 and then s 48
Powers in relatior	to serious electrical accidents
s 89M	renum as s 103 and then s 49
Powers in relatior	to unsafe articles of electrical equipment
s 89N	renum as s 104 and then s 50
Labelling defectiv	e electrical equipment
s 89P	renum as s 105 and then s 51
Power to require I	name and address
s 89Q	renum as s 106 and then s 52
Power to seize ev	idence
s 89R	renum as s 107 and then s 53

page 98

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

Amendment history 4

Receipt for things seized s 89S renum as s 108 and then s 54 Access to things seized s 89T renum as s 109 and then s 55 Return of things seized s 89U renum as s 110 and then s 56 Power to inspect electrical wiring work s 89V renum as s 111 and then s 57 Self-incrimination etc s 89W renum as s 112 and then s 58 Legal professional privilege s 89X renum as s 113 Providing false or misleading information s 89Y renum as s 114 Providing false or misleading documents s 89Z renum as s 115 **Obstruction of inspectors** s 89ZA renum as s 116 Damage etc to be minimised s 89ZB renum as s 117 and then s 59 Compensation s 89ZC renum as s 118 and then s 60 Publication of report of serious electrical accident (prev s 33) am Ord1972-27 s 6; Ord1982-61 s 2; s 90 Ord1985-67 sch pt 1; Ord1989-38 sch 1; A1994-52 s 33, sch renum as s 90 A1994-52 s 48 am A1994-81 sch; A2000-69 sch 1 om A2000-66 sch 1 pt 4 (prev s 88) renum as s 90 and then s 36 Enforcement pt 11 hdg orig pt 11 hdg ins A2000-69 s 27 exp 20 June 2001 (s 108) (prev pt 7D hdg) renum as pt 11 hdg and then pt 7 hdg General div 11.1 hdg (prev pt 7D div 1 hdg) renum as div 11.1 hdg and then div 7.1 hdg

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 99

4 Amendment history

s 91	<i>iness premises</i> (prev s 34) am Ord1988-31 sch; A1994-52 sch renum as s 91 A1994-52 s 48 am A1994-81 sch; A1998-51 s 6 om A2000-69 s 24 (prev s 89) renum as s 91 and then s 37
Things connecte s 92	d with offences (prev s 35) am A1994-52 sch renum as s 92 A1994-52 s 48 am A1994-81 sch om A2000-69 s 24 (prev s 89A) renum as s 92 and then s 38
Planning and lan s 93	d authority may require information and document (prev s 36) am A1994-52 sch renum as s 93 A1994-52 s 48 am A1994-81 sch; A2000-69 sch 1 om A2000-66 sch 1 pt 4 (prev s 89B) renum as s 93 and then s 39
Contravention of s 94	f requirement by planning and land authority (prev s 36AA) renum as s 94 and then s 119 and the s 61 (prev s 89C) renum as s 94 and then s 40
Appointment of i s 95	nspectors (prev s 36AB) renum as s 95 and then s 120 and the s 62 (prev s 89D) renum as s 95 and then s 41
Identity cards s 96	(prev s 36A) renum as s 96 and then s 121 (prev s 89E) renum as s 96 and then s 42
Inspectors' powe div 11.2 hdg	ers (prev pt 7D div 2 hdg) renum as div 11.2 hdg and the div 7.2 hdg
General power to s 97	b enter premises (prev s 37) renum as s 97 and then s 122 (prev s 89F) renum as s 97 and then s 43
Production of ide s 98	entity card (prev s 38) renum as s 98 and then s 123 (prev s 89G) renum as s 98 and then s 44
	,

page 100

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

		Amendment hist	ory 4
	Warrants		
	s 100	(prev s 40) renum as s 100 and then s 125 (prev s 89J) renum as s 100 and then s 46	
	Warrants—applie s 101	cation made other than in person (prev s 41) renum as s 101 and then s 126 a (prev s 89K) renum as s 101 and then s 47	nd then s 63
	Powers on entry s 102	to premises (prev s 42) renum as s 102 and then s 127 (prev s 89L) renum as s 102 and then s 48	
	Powers in relatic s 103	n to serious electrical accidents (prev s 43) am A1994-52 sch renum as s 103 A1994-52 s 48 om A2000-69 sch 1 ins A2001-44 amdt 1.1451 renum as s 128 (prev s 89M) renum as s 103 and then s 49	
	Powers in relatic s 104	on to unsafe articles of electrical equipment (prev s 43AA) renum as s 104 and then s 129 s 65 (prev s 89N) renum as s 104 and then s 50	9 and then
	Disconnecting e s 105	tc dangerous electrical equipment and insta (prev s 43A) ins Ord1988-31 sch renum as s 105 A1994-52 s 48 om A2000-69 sch 1 (prev s 89P) renum as s 105 and then s 51	llations
	Power to require s 106	name and address (prev s 44) am Ord1989-38 sch 1 renum as s 106 A1994-52 s 48 om A2001-44 amdt 1.1451 (prev s 89Q) renum as s 106 and then s 52	
	Power to seize e s 107	vidence orig s 107 ins A2000-69 s 27 exp 20 June 2001 (s 108) (prev s 89R) renum as s 107 and then s 53	
	Receipt for thing s 108	s seized orig s 108 ins A2000-69 s 27 exp 20 June 2001 (s 108) (prev s 89S) renum as s 108 and then s 54	
	Access to things s 109	s seized (prev s 89T) renum as s 109 and then s 55	
	Return of things s 110	seized (prev s 89U) renum as s 110 and then s 56	
14		Electricity Safety Act 1971 Effective: 06/03/14-17/04/14	page 101

Authorised by the ACT Parliamentary Counsel-also accessible at www.legislation.act.gov.au

R23

06/03/14

4	Amendment history	
---	-------------------	--

Power to inspect s 111	electrical wiring work (prev s 89V) renum as s 111 and then s 57
Miscellaneous div 11.3 hdg	(prev pt 7D div 3 hdg) renum as div 11.3 hdg and then div 7.3 hdg
Self-incriminatior s 112) etc (prev s 89W) renum as s 112 and then s 58
Legal professiona s 113	al privilege (prev s 89X) ins A2000-69 s 23 renum as s 113 R4 LA (see A2000-69 s 29) om A2002-11 amdt 2.38
Providing false of s 114	r misleading information (prev s 89Y) ins A2000-69 s 23 renum as s 114 R4 LA (see A2000-69 s 29) om A2004-15 amdt 2.67
Providing false o s 115	r misleading documents (prev s 89Z) ins A2000-69 s 23 renum as s 115 R4 LA (see A2000-69 s 29) om A2004-15 amdt 2.67
Obstruction of in s 116	spectors (prev s 89ZA) ins A2000-69 s 23 renum as s 116 R4 LA (see A2000-69 s 29) om A2004-15 amdt 2.67
Damage etc to be s 117	e minimised (prev s 89ZB) renum as s 117 and then s 59
Compensation s 118	(prev s 89ZC) renum as s 118 and then s 60
Appeals pt 12 hdg	(prev pt 8A hdg) renum as pt 9 hdg and then pt 12 hdg and then pt 8 hdg
Review of decision	-
s 119	(prev s 36AA) renum as s 94 and then s 119 and then s 61
Notifications of d s 120	ecisions (prev s 36AB) renum as s 95 and then s 120 and then s 62
Miscellaneous pt 13 hdg	(prev pt 9 hdg) renum as pt 10 hdg and then pt 13 hdg and then pt 9 hdg

page 102

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

	Amenument histo	ry 2
Conduct of dire	ctors, servants and agents	
s 121	(prev s 36A) ins Ord1987-5 s 17 renum as s 96 A1994-52 s 48 renum as s 121 R4 LA (see A2000-69 s 29) om A2004-15 amdt 1.13	
Production of li	cence or permit for inspection	
s 122	(prev s 37) am A1994-52 s 35, sch renum as s 97 A1994-52 s 48 am A1994-81 sch; A2000-69 sch 1 renum as s 122 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.34	
Change of name s 123	(prev s 38) am A1994-52 s 36, sch renum as s 98 A1994-52 s 48 am A1994-81 sch	
	renum as s 123 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.34	
Loss etc of licer	nce or permit	
s 124	(prev s 39) am A1994-52 s 37, sch	
	renum as s 99 A1994-52 s 48 am A2001-44 amdt 1. 1449, amdt 1.1450	
	renum as s 124 R4 LA (see A2000-69 s 29)	
	om A2004-13 amdt 2.34	
Expired licences	s or permits	
s 125	(prev s 40) am A1994-52 s 38, sch	
	renum as s 100 A1994-52 s 48 am A1994-81 sch	
	renum as s 125 R4 LA (see A2000-69 s 29)	
	om A2004-13 amdt 2.34	
Evidence	(11) 101 11 100	
s 126	(prev s 41) renum as s 101 and then s 126 an	d then s b
Service of notic s 127	es (prev s 42) am A1994-52 s 40	
0 121	renum as s 102 A1994-52 s 48	
	renum as s 127 R4 LA (see A2000-69 s 29) om A2004-13 amdt 2.36	
Determination o		
	(prev s 103) renum as s 128 and then s 64	
Approved forms	5	
s 129	(prev s 43AA) renum as s 104 and then s 129 s 65	and then
Regulation-mak	•	
s 130	(prev s 105) renum as s 130 and then s 66	
	Electricity Sofety Act 1071	nogo 10
	Electricity Safety Act 1971	page 10

R23 06/03/14

Effective: 06/03/14-17/04/14

4 Amendment history

New regulations s 131 renum as s 67 **Reviewable decisions** sch 1 ins A2008-37 amdt 1.155 Dictionary dict ins A2004-13 amdt 2.38 am A2006-15 amdt 1.28; A2007-39 amdt 3.40; A2008-37 amdt 1.156; A2009-20 amdt 3.66; A2009-49 amdt 3.56; A2012-21 amdt 3.67 def approved first seller ins A2007-39 amdt 3.41 def article of electrical equipment ins A2004-13 amdt 2.38 am A2007-39 amdt 3.42 def AS/NZS 3000 ins A2004-13 amdt 2.38 def AS/NZS 3017 ins A2004-13 amdt 2.38 def AS/NZS 3820 ins A2004-13 amdt 2.38 def business premises ins A2007-39 amdt 3.43 def connected with ins A2007-39 amdt 3.43 def corresponding law ins A2007-39 amdt 3.43 def declaration of compliance ins A2007-39 amdt 3.43 def electrical installation ins A2004-13 amdt 2.38 sub A2011-23 s 9 def electrical wiring work ins A2004-13 amdt 2.38 def electricity distributor ins A2004-13 amdt 2.38 def electricity network ins A2004-13 amdt 2.38 def engage in conduct ins A2005-54 amdt 1.132 def generator ins A2011-23 s 10 def inspector ins A2004-13 amdt 2.38 sub A2007-39 amdt 3.44 def occupier ins A2004-13 amdt 2.38 def offence ins A2007-39 amdt 3.45 def premises ins A2004-13 amdt 2.38 def prescribed article of electrical equipment ins A2004-13 amdt 2.38 sub A2006-15 amdt 1.29 def prohibited ins A2004-13 amdt 2.38 sub A2007-39 amdt 3.46 def regulatory authority ins A2004-13 amdt 2.38 sub A2013-31 s 76 def relevant distributor ins A2007-39 amdt 3.47 def relevant safety standard ins A2007-39 amdt 3.47 def relevant standard ins A2004-13 amdt 2.38 def reviewable decision ins A2008-37 amdt 1.157

page 104

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 R23 06/03/14

Amendment history 4

def *sell* ins A2004-13 amdt 2.38 def *serious electrical accident* ins A2004-13 amdt 2.38 om R15 LA ins A2007-39 amdt 3.47

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 105

5 Earlier republications

5 Earlier republications

Some earlier republications were not numbered. The number in column 1 refers to the publication order.

Since 12 September 2001 every authorised republication has been published in electronic pdf format on the ACT legislation register. A selection of authorised republications have also been published in printed format. These republications are marked with an asterisk (*) in column 1. Electronic and printed versions of an authorised republication are identical.

Republication No	Amendments to	Republication date
1	A1991-3	31 January 1993
2	A1994-81	31 January 1995
3	A1997-96	1 June 1998
4	A2001-44	12 September 2001
5	A2001-44	9 May 2002
6*	A2002-11	29 May 2002
7	A2002-51	1 January 2003
7 (RI)	A2002-51 ‡	10 February 2003
8	A2003-37	1 November 2003
9	A2004-15	9 April 2004
10	A2004-15	1 September 2004
11	A2004-15	2 September 2004
12	A2005-54	24 November 2005
13	A2005-54	25 November 2005
14	A2006-15	1 September 2006
15	A2007-39	27 December 2007
16	A2008-37	2 February 2009
17*	A2009-20	22 September 2009
18	A2009-49	17 December 2009
19	A2011-23	7 July 2011
20	A2012-21	5 June 2012

page 106

Electricity Safety Act 1971 Effective: 06/03/14-17/04/14

		Renumbered provisions	
Republication No	Amendments to	Republication da	te
21	A2012-32	1 July 2012	
22	A2013-31	27 August 2013	

‡ includes retrospective amendments by A2002-49

6

Renumbered provisions

This Act was renumbered by *Electricity (Amendment) Act 1994* A1994-52 s 48 and *Electricity Amendment Act 2000* A2000-69 s 29. Details of the renumbered provisions are shown in endnote 4 (Amendment history) and endnote 6 (Renumbered provisions) in R4. It was also renumbered under the *Legislation Act 2001*, in R10 (see *Construction Occupations Legislation Amendment Act 2004* A2004-13 amdt 2.43). For a table showing the renumbered provisions, see R13.

© Australian Capital Territory 2014

R23 06/03/14 Electricity Safety Act 1971 Effective: 06/03/14-17/04/14 page 107